

User Guide

MD290 Series AC Drive



## Preface

Thank you for purchasing the MD290 series AC drive developed by Inovance.

It is a general-purpose AC drive mainly used for controlling and adjusting the speed and torque of three-phase AC asynchronous motors. MD290 provides user-programmable features and software tool monitoring and communication bus functions, delivering rich and powerful combined functions and stable performance. It can be used to drive textile, papermaking, drawing, machine tools, packaging, foods, fans, water pumps and other automated production equipment.



Product appearance

### ■ First use

Read this user guide carefully if you use the AC drive for the first time. For any doubt on its function or performance, contact our technicians for help.

### ■ Standards compliance

The following table lists the certifications and standards that the product may comply with. For details about the acquired certificates, see the certification marks on the product nameplate.

Name	Directive Name		Standard
CE certification	EMC directive	2014/30/EU	EN 61800-3
	LVD directive	2014/35/EU	EN 61800-5-1
	RoHS directive	2011/65/EU	EN 50581
TUV certification	-		EN 61800-5-1
UL certification	-		UL61800-5-1 C22.2 No.14-13



■ Adjusting drive parameters

The drive when it leaves the factory with default settings should enable the user to get started quickly to check on the basic mechanical running conditions. At a later time, fine tuning to optimize the operation/performance can be undertaken.

Such parameter tuning should be done by qualified personnel who have prior training on Servo Drives. Some parameter settings can have adverse reactions if manipulated incorrectly and care should be taken especially during the commissioning startup stages to prevent personnel from engaging the machine.

This user guide provides a complete list of the parameters with functional description and care should always be taken whenever parameters are adjusted during a live running startup. Inovance and Authorized Distributors can provide product training and if in doubt seek advice.

## Revision History

Date	Version	Change Description
November 2015	V0.0	◆ Related firmware version: F7-10 = U29.06 and F7-11 = U29.15
September 2016	A01	◆ Added large power rating data. ◆ F7-10 = U29.07 F7-11 = U29.16
November 2016	A02	◆ Modified Approvals, designation rule and nameplate data.
November 2017	A03	◆ Added data of the 0.4 to 15 kW models. ◆ Deleted data of the MDKE7 operating panel and added data of the MDKE9 operating panel.
July 2019	A04	<ul style="list-style-type: none"> <li>◆ Changed the structure of the user guide.</li> <li>◆ Added data of the three-phase 200 to 240 V models in the following sections:               <ol style="list-style-type: none"> <li>1) 1.1 Nameplate and Model Number</li> <li>2) 1.3 Technical Data</li> <li>3) 1.4 Overall Dimensions</li> <li>4) 2.4 Selection of Cables, Breakers, and Contactors</li> <li>5) 2.5 Selection of the AC Output Reactor</li> <li>6) 2.6 Selection of Braking Components</li> <li>7) 3.1.2 Backplate Mounting and Through Hole Mounting (Note: The three-phase 200 to 240 V models include MD290-2T0.4G/0.7PB to MD290-2T55G/75P.)</li> </ol> </li> <li>◆ Added data of cables that comply with UL certifications in "2.4 Selection of Cables, Breakers, and Contactors".</li> <li>◆ Added model selection data of braking components in "2.6 Selection of Braking Components".</li> <li>◆ Updated Inovance's logo.</li> </ul>
July 2020	A05	<ul style="list-style-type: none"> <li>◆ Deleted the service hotline.</li> <li>◆ Added information of F3-09.</li> </ul>

### ■ User guide and acquisition

This user guide is shipped with the product. For any additional order, contact your sales representative.

This user guide briefly introduces product information, installation and wiring, troubleshooting, and routine maintenance. For more details, see 19010321 MD290 Series AC Drive Advanced User Guide.

To obtain the user guide, access Inovance's website (<http://www.inovance.com>), click "Download", search for the user guide by its name, and then download the PDF file.

# Safety Instructions

## Safety Precautions

- 1) Before installing, using, and maintaining this equipment, read the safety information and precautions thoroughly, and comply with them during operations.
- 2) To ensure the safety of humans and equipment, follow the signs on the equipment and all the safety instructions in this user guide.
- 3) "CAUTION", "WARNING", and "DANGER" items in the user guide do not indicate all safety precautions that need to be followed; instead, they just supplement the safety precautions.
- 4) Use this equipment according to the designated environment requirements. Damage caused by improper usage is not covered by warranty.
- 5) Inovance shall take no responsibility for any personal injuries or property damage caused by improper usage.

## Safety Levels and Definitions



indicates that failure to comply with the notice will result in severe personal injuries or even death.



indicates that failure to comply with the notice may result in severe personal injuries or even death.



indicates that failure to comply with the notice may result in minor personal injuries or damage to the equipment.

## Safety Instructions

Unpacking	
	<ul style="list-style-type: none"><li>◆ Check whether the packing is intact and whether there is damage, water seepage, damp, and deformation.</li><li>◆ Unpack the package by following the package sequence. Do not hit the package with force.</li><li>◆ Check whether there are damage, rust, or injuries on the surface of the equipment or equipment accessories.</li><li>◆ Check whether the number of packing materials is consistent with the packing list.</li></ul>

**WARNING**

- ◆ Do not install the equipment if you find damage, rust, or indications of use on the equipment or accessories.
- ◆ Do not install the equipment if you find water seepage, component missing or damage upon unpacking.
- ◆ Do not install the equipment if you find the packing list does not conform to the equipment you received.

## Storage and Transportation

**CAUTION**

- ◆ Store and transport this equipment based on the storage and transportation requirements for humidity and temperature.
- ◆ Avoid transporting the equipment in environments such as water splashing, rain, direct sunlight, strong electric field, strong magnetic field, and strong vibration.
- ◆ Avoid storing this equipment for more than three months. Long-term storage requires stricter protection and necessary inspections.
- ◆ Pack the equipment strictly before transportation. Use a sealed box for long-distance transportation.
- ◆ Never transport this equipment with other equipment or materials that may harm or have negative impacts on this equipment.

**WARNING**

- ◆ Use professional loading and unloading equipment to carry large-scale or heavy equipment.
- ◆ When carrying this equipment with bare hands, hold the equipment casing firmly with care to prevent parts falling. Failure to comply may result in personal injuries.
- ◆ Handle the equipment with care during transportation and mind your step to prevent personal injuries or equipment damage.
- ◆ Never stand or stay below the equipment when the equipment is lifted by hoisting equipment.

## Installation

**WARNING**

- ◆ Thoroughly read the safety instructions and user guide before installation.
- ◆ Do not modify this equipment.
- ◆ Do not rotate the equipment components or loosen fixed bolts (especially those marked in red) on equipment components.
- ◆ Do not install this equipment in places with strong electric or magnetic fields.
- ◆ When this equipment is installed in a cabinet or final equipment, protection measures such as a fireproof enclosure, electrical enclosure, or mechanical enclosure must be provided. The IP rating must meet IEC standards and local laws and regulations.



- ◆ Equipment installation, wiring, maintenance, inspection, or parts replacement must be performed by only professionals.
- ◆ Installation, wiring, maintenance, inspection, or parts replacement must be performed by only experienced personnel who have been trained with necessary electrical information.
- ◆ Installation personnel must be familiar with equipment installation requirements and relevant technical materials.
- ◆ Before installing equipment with strong electromagnetic interference, such as a transformer, install an electromagnetic shielding device for this equipment to prevent malfunctions.

### Wiring



- ◆ Equipment installation, wiring, maintenance, inspection, or parts replacement must be performed by only professionals.
- ◆ Never perform wiring at power-on. Failure to comply will result in an electric shock.
- ◆ Before wiring, cut off all equipment power supplies. Wait at least 10 minutes before further operations because residual voltage exists after power-off.
- ◆ Make sure that the equipment is well grounded. Failure to comply will result in an electric shock.
- ◆ During wiring, follow the proper electrostatic discharge (ESD) procedures, and wear an antistatic wrist strap. Failure to comply will result in damage to internal equipment circuits.



- ◆ Never connect the power cable to output terminals of the equipment. Failure to comply may cause equipment damage or even a fire.
- ◆ When connecting a drive with the motor, make sure that the phase sequences of the drive and motor terminals are consistent to prevent reverse motor rotation.
- ◆ Wiring cables must meet diameter and shielding requirements. The shielding layer of the shielded cable must be reliably grounded at one end.
- ◆ After wiring, make sure that no screws are fallen and cables are exposed in the equipment.

## Power-on



- ◆ Before power-on, make sure that the equipment is installed properly with reliable wiring and the motor can be restarted.
- ◆ Before power-on, make sure that the power supply meets equipment requirements to prevent equipment damage or even a fire.
- ◆ At power-on, unexpected operations may be triggered on the equipment. Therefore, stay away from the equipment.
- ◆ After power-on, do not open the cabinet door and protective cover of the equipment. Failure to comply will result in an electric shock.
- ◆ Do not touch any wiring terminals at power-on. Failure to comply will result in an electric shock.
- ◆ Do not remove any part of the equipment at power-on. Failure to comply will result in an electric shock.

## Operation



- ◆ Do not touch any wiring terminals during operation. Failure to comply will result in an electric shock.
- ◆ Do not remove any part of the equipment during operation. Failure to comply will result in an electric shock.
- ◆ Do not touch the equipment shell, fan, or resistor for temperature detection. Failure to comply will result in heat injuries.
- ◆ Signal detection must be performed by only professionals during operation. Failure to comply will result in personal injuries or equipment damage.



- ◆ Prevent metal or other objects from falling into the device during operation. Failure to comply may result in equipment damage.
- ◆ Do not start or stop the equipment using the contactor. Failure to comply may result in equipment damage.

## Maintenance



- ◆ Equipment installation, wiring, maintenance, inspection, or parts replacement must be performed by only professionals.
- ◆ Do not maintain the equipment at power-on. Failure to comply will result in an electric shock.
- ◆ Before maintenance, cut off all equipment power supplies and wait at least 10 minutes.



- ◆ Perform daily and periodic inspection and maintenance for the equipment according to maintenance requirements and keep a maintenance record.

Repair



- ◆ Equipment installation, wiring, maintenance, inspection, or parts replacement must be performed by only professionals.
- ◆ Do not repair the equipment at power-on. Failure to comply will result in an electric shock.
- ◆ Before inspection and repair, cut off all equipment power supplies and wait at least 10 minutes.



- ◆ Require repair services according to the product warranty agreement.
- ◆ When the equipment is faulty or damaged, require professionals to perform troubleshooting and repair by following repair instructions and keep a repair record.
- ◆ Replace quick-wear parts of the equipment according to the replacement guide.
- ◆ Do not operate damaged equipment. Failure to comply may result in worse damage.
- ◆ After the equipment is replaced, perform wiring inspection and parameter settings again.

Disposal



- ◆ Retire equipment by following local regulations or standards. Failure to comply may result in property damage, personal injuries, or even death.
- ◆ Dispose of or recycle retired equipment by following industry waste disposal standards to avoid environmental pollution.

## Safety Signs

- Description of safety signs in the user guide



Read the user guide before installation and operation.



Reliably ground the system and equipment.



Danger!



High temperature!



Prevent personal injuries caused by machines.



High voltage!



Wait xx minutes before further operations.

- Description of safety signs on the equipment

For safe equipment operation and maintenance, comply with safety signs on the equipment, and do not damage or remove the safety labels. The following table describes the safety signs.

Safety Sign	Description
	<ul style="list-style-type: none"> <li>◆ Read the user guide before installation and operation. Failure to comply will result in an electric shock.</li> <li>◆ Do not remove the cover at power-on or within 10 minutes after power-off.</li> <li>◆ Before maintenance, inspection, and wiring, cut off input and output power, and wait at least 10 minutes until the power indicator is off.</li> </ul>

# Contents


Preface .....	1
Revision History .....	3
Safety Instructions .....	4
Safety Precautions.....	4
Safety Levels and Definitions .....	4
Safety Instructions.....	4
Safety Signs.....	9
1 Product Information.....	12
1.1 Nameplate and Model Number .....	12
1.2 Components .....	13
1.3 Technical Data.....	15
1.4 Overall Dimensions.....	23
1.4.1 Overall Dimensions of MD290T0.4G/0.7PB to MD290T160G/200P and MD290-2T0.4G/0.7PB to MD290-2T55G/75P .....	23
1.4.2 Overall Dimensions of MD290T200G to MD290T450G and MD290T220P to MD290T500P.....	25
1.4.3 Overall Dimensions of MD290T200G-L to MD290T450G-L and MD290T220P-L to MD290T500P-L.....	26
2 System Connections.....	27
2.1 Connection Diagram.....	27
2.2 System Structure .....	28
2.3 Options .....	30
2.4 Selection of Cables, Breakers, and Contactors .....	32
2.5 Selection of the AC Output Reactor.....	35
2.6 Selection of Braking Components.....	36
2.7 External Operating Panels.....	39
3 Installation and Wiring .....	42
3.1 Installation .....	42
3.1.1 Installation Environment .....	42
3.1.2 Backplate Mounting and Through-Hole Mounting.....	43
3.1.3 Mounting in the Cabinet.....	46
3.2 Wiring.....	49
3.2.1 Standard Wiring Diagram.....	49
3.2.2 Main Circuit Terminals .....	50

---

3.2.3 Control Circuit Terminals .....	51
4 Panel Operations .....	55
4.1 Introduction .....	55
4.2 Keys on the Operating Panel.....	55
4.3 Indicators on the Operating Panel.....	56
5 Basic Operations and Trial Run .....	57
5.1 Quick Commissioning .....	57
5.2 Precautions Before Power-on.....	57
5.3 Status Display After Power-on .....	58
5.4 Parameter Initialization.....	58
5.5 Motor Control Modes.....	59
5.6 Auto-tuning .....	59
6 Troubleshooting .....	61
6.1 Fault Codes and Solutions .....	61
6.2 Common Symptoms and Solutions.....	67
7 Maintenance.....	70
7.1 Routine Maintenance .....	70
7.2 Periodic Inspection.....	71
7.3 Replacement of Wear Parts.....	71
7.3.1 Service Life of Wear Parts.....	71
7.3.2 Replacing Cooling Fans .....	72
7.4 Storage .....	73
Appendix A Parameter Table .....	74
A.1 Standard Parameter Table .....	74
A.2 Monitoring Parameters .....	99
Warranty Agreement.....	101

# 1 Product Information

## 1.1 Nameplate and Model Number



**MD290 T 18.5 G/22 P B**

Mark	Product Name
MD290	AC drive series

Mark	Voltage Class
T	Three phase 380-480 V
2T	Three phase 200-240 V

Mark	Power Rating (kW)
0.4	0.4
...	...
450	450

Mark	Applicable Motor
P	Fan, water pump
G	General-purpose

Mark	Reactor
Blank	None
-L	Output AC reactor, applicable to MD290T200G-L to MD290T450G-L, MD290T220P-L to MD290T500P-L
-T	DC reactor, applicable to MD290T18.5G/22P to MD290T22G/30P

Mark	Braking Unit
Blank	None
B	Braking unit included

Figure 1-1 Nameplate and model number

## 1.2 Components

The AC drive has either a plastic housing (three-phase 380 to 480 V, 0.4 to 15 kW models and three-phase 200 to 240 V, 0.4 to 7.5 kW models used as an example) or a sheet metal housing (200 to 450 kW models used as an example), depending on the voltage and power rating, as shown in the following figures.




Figure 1-2 Components (MD290T0.4G/0.7PB to MD290T15G/18.5PB, MD290-2T0.4G/0.7PB to MD290-2T7.5G/11PB)

# 1 Product Information




Figure 1-3 Components (Three-phase 380–480 V, MD290T200G to MD290T450G, MD290T220P to MD290T500P)

## 1.3 Technical Data

Table 1-1 MD290TXXP models and technical data (three-phase 380–480 V)

Item		Specification														
MD290TXXP		0.7	1.1	1.5	2.2	3.0	3.7	5.5	7.5	11	15	18.5	22	30	37	45
Output	Applicable Motor (kW)	0.75	1.1	1.5	2.2	3.0	3.7	5.5	7.5	11	15	18.5	22	30	37	45
	Rated Output Current (A)	2.1	3.1	3.8	5.1	7.2	9	13	17	25	32	37	45	60	75	91
	Output Voltage	0 to input voltage														
	Maximum Output Frequency	500 Hz (editable through a parameter)														
	Carrier Frequency	0.8 to 8.0 kHz (automatically adjusted according to the temperature)														
	Overload Capacity	130% for 60s with rated current														
Input	Rated Input Current (A)	2.5	3.7	4.6	6.4	9.1	11.3	15.9	22.4	32.9	39.7	44	59	65.8	71	86
	Rated Input Voltage	Three-phase 380 to 480 VAC, 50/60 Hz														
	Allowed Voltage Fluctuation	-15% to +10%; actual allowed range: 323–528 VAC														
	Allowed Frequency Fluctuation	±5%														
	Power Capacity (kVA)	2.3	3.4	4.2	5.9	8.3	10.4	15.5	20.5	30.2	38.2	44.4	54	60	65	79
Thermal Design	Thermal Power Consumption (kW)	0.048	0.060	0.068	0.088	0.112	0.140	0.207	0.273	0.388	0.491	0.561	0.616	0.76	0.85	1.04
	Air Flow (CFM)	-	-	-	9	9	9	20	24	30	40	42	51.9	57.4	118.5	118.5
IP Rating		IP20														

Item		Specification															
MD290TXXP		55	75	90	110	132	160	200	220	250	280	315	355	400	450	500	
Output	Applicable Motor (kW)	55	75	90	110	132	160	200	220	250	280	315	355	400	450	500	
	Rated Output Current (A)	112	150	176	210	253	304	377	426	465	520	585	650	725	820	880	
	Output Voltage	Three-phase 380 to 480 V (proportional to input voltage)															
	Maximum Output Frequency	500 Hz (editable through a parameter)															
	Carrier frequency	0.8–8.0 kHz					0.8–6.0 kHz										
	Overload Capacity	Automatically adjusted according to the temperature															
		130% for 60s with rated current															

## 1 Product Information

Item		Specification														
MD290TXXP		55	75	90	110	132	160	200	220	250	280	315	355	400	450	500
Input	Rated Input Current (A)	111	143	167	198	239	295	359	410	456	507	559	624	708	782	840
	Rated Input Voltage	Three-phase 380 to 480 VAC, 50/60 Hz														
	Allowed Voltage Fluctuation	-15% to +10%; actual allowed range: 323–528 VAC														
	Allowed Frequency Fluctuation	±5%														
	Power Capacity (kVA)	102	131	153	181	219	270	328	375	417	464	511	571	647	715	768
Thermal Design	Thermal Power Consumption (kW)	1.22	1.61	1.91	2.22	2.67	3.61	4.68	5.27	5.74	6.63	7.14	7.52	8.62	8.97	9.60
	Air Flow (CFM)	122.2	122.2	218.6	287.2	354.2	547	627	638.4	722.5	789.4	882	645	860	860	860
IP Rating		IP20						IP00								



### NOTE

- ◆ The rated power is measured at 440 VAC input voltage.

Table 1-2 MD290-2TXXP models and technical data (three-phase 200–240 V)

Item		Specification															
MD290-2TXXP		0.7	1.1	1.5	2.2	3.7	5.5	7.5	11	15	18.5	22	30	37	45	55	75
Output	Applicable Motor (kW)	0.75	1.1	1.5	2.2	3.7	5.5	7.5	11	15	18.5	22	30	37	45	55	75
	Rated Output Current (A)	3.1	5.1	7.2	9	13	17	32	37	60	75	91	112	150	176	210	253
	Output Voltage	0 to input voltage															
	Maximum Output Frequency	500 Hz (editable through a parameter)															
	Carrier Frequency	0.8 to 8.0 kHz (automatically adjusted according to the temperature)															
	Overload Capacity	130% for 60s with rated current															
Input	Rated Input Current (A)	3.7	6.4	9.1	11.3	15.9	22.4	39.7	44	71	71	86	111	143	167	198	239
	Rated Input Voltage	Three-phase 200 to 240 VAC, 50/60 Hz															
	Allowed Voltage Fluctuation	-15% to +10%; actual allowed range: 170–264 VAC															
	Allowed Frequency Fluctuation	±5%															
	Power Capacity (kVA)	3.4	5.9	8.3	10.4	15.5	20.5	38.2	44.4	60	65	79	102	131	153	181	219

Item		Specification															
MD290-2TXXP		0.7	1.1	1.5	2.2	3.7	5.5	7.5	11	15	18.5	22	30	37	45	55	75
Thermal Design	Thermal Power Consumption (kW)	0.060	0.088	0.112	0.140	0.207	0.273	0.491	0.561	0.76	0.85	1.04	1.22	1.61	1.91	2.22	2.67
	Air Flow (CFM)	-	9	9	9	20	24	40	42	57.4	118.5	118.5	122.2	122.2	218.6	287.2	354.2
IP Rating		IP20															



## NOTE

◆ The rated power is measured at 220 VAC input voltage.

Table 1-3 MD290TXXG models and technical data (three-phase 380–480 V)

Item		Specification														
MD290TXXG		0.4	0.7	1.1	1.5	2.2	3.0	3.7	5.5	7.5	11	15	18.5	22	30	37
Output	Applicable Motor (kW)	0.4	0.75	1.1	1.5	2.2	3.0	3.7	5.5	7.5	11	15	18.5	22	30	37
	Rated Output Current (A)	1.5	2.1	3.1	3.8	5.1	7.2	9.0	13.0	17.0	25.0	32.0	37	45	60	75
	Output Voltage	0 to input voltage														
	Maximum Output Frequency	500 Hz (editable through a parameter)														
	Carrier Frequency	0.8 to 8.0 kHz (automatically adjusted according to the temperature)														
	Overload Capacity	150% for 60s with rated current (MD290T450G: 130% for 60s with rated current)														
	Rated Input Current (A)	1.8	2.4	3.7	4.6	6.3	9.0	11.4	16.7	21.9	32.2	41.3	49.5	59	57	69
Input	Rated Input Voltage	Three-phase 380 to 480 VAC, 50/60 Hz														
	Allowed Voltage Fluctuation	-15% to +10%; actual allowed range: 323–528 VAC														
	Allowed Frequency Fluctuation	±5%														
	Power Capacity (kVA)	2	2.8	4.1	5	6.7	9.5	12	17.5	22.8	33.4	42.8	45	54	52	63
	Thermal Power Consumption (kW)	0.039	0.046	0.057	0.068	0.081	0.109	0.138	0.201	0.24	0.355	0.454	0.478	0.551	0.694	0.815
Thermal Design	Air Flow (CFM)	-	-	-	9	9	9	20	24	30	40	42	51.9	57.4	118.5	118.5
	IP Rating	IP20														

## 1 Product Information

Item		Specification														
MD290TXXG		45	55	75	90	110	132	160	200	220	250	280	315	355	400	450
Output	Applicable Motor (kW)	45	55	75	90	110	132	160	200	220	250	280	315	355	400	450
	Rated Output Current (A)	91	112	150	176	210	253	304	377	426	465	520	585	650	725	820
	Output Voltage	Three-phase 380 to 480 V (proportional to input voltage)														
	Maximum Output Frequency	500 Hz (editable through a parameter)														
	Carrier frequency	0.8–8.0 kHz				0.8–6.0 kHz										
		Automatically adjusted according to the temperature														
	Overload Capacity	150% for 60s with rated current (MD290T450G: 130% for 60s with rated current)														
Input	Rated Input Current (A)	89	106	139	164	196	240	287	365	410	441	495	565	617	687	782
	Rated Input Voltage	Three-phase 380 to 480 VAC, 50/60 Hz														
	Allowed Voltage Fluctuation	-15% to +10%; actual allowed range: 323–528 VAC														
	Allowed Frequency Fluctuation	±5%														
	Power Capacity (kVA)	81	97	127	150	179	220	263	334	375	404	453	517	565	629	716
Thermal Design	Thermal Power Consumption (kW)	1.01	1.21	1.57	1.81	2.14	2.85	3.56	4.15	4.55	5.06	5.33	5.69	6.31	6.91	7.54
	Air Flow (CFM)	122.2	122.2	218.6	287.2	354.2	547	627	638.4	722.5	789.4	882	645	860	860	860
IP Rating		IP20						IP00								



### NOTE

- ◆ The rated power is measured at 440 VAC input voltage.

Table 1-4 MD290-2TXXG models and technical data (three-phase 200–240 V)

Item		Specification															
MD290-2TXXG		0.4	0.7	1.1	1.5	2.2	3.7	5.5	7.5	11	15	18.5	22	30	37	45	55
Output	Applicable Motor (kW)	0.4	0.75	1.1	1.5	2.2	3.7	5.5	7.5	11	15	18.5	22	30	37	45	55
	Rated Output Current (A)	2.1	3.8	5.1	7.2	9.0	13.0	25.0	32.0	45	60	75	91	112	150	176	210
	Output Voltage	0 to input voltage															
	Maximum Output Frequency	500 Hz (editable through a parameter)															
	Carrier Frequency	0.8 to 8.0 kHz (automatically adjusted according to the temperature)															
	Overload Capacity	150% for 60s with rated current															
Input	Rated Input Current (A)	2.4	4.6	6.3	9.0	11.4	16.7	32.2	41.3	59	57	69	89	106	139	164	196
	Rated Input Voltage	Three-phase 200 to 240 VAC, 50/60 Hz															
	Allowed Voltage Fluctuation	-15% to +10%; actual allowed range: 170–264 VAC															
	Allowed Frequency Fluctuation	±5%															
	Power Capacity (kVA)	2.8	5	6.7	9.5	12	17.5	33.4	42.8	54	52	63	81	97	127	150	179
Thermal Design	Thermal Power Consumption (kW)	0.046	0.068	0.081	0.109	0.138	0.201	0.355	0.454	0.551	0.694	0.815	1.01	1.21	1.57	1.81	2.14
	Air Flow (CFM)	-	9	9	9	20	24	40	42	57.4	118.5	118.5	122.2	122.2	218.6	287.2	354.2
IP Rating		IP20															

**NOTE**

- ◆ The rated power is measured at 220 VAC input voltage.

Table 1-5 Technical specifications of the MD290 series AC drive

	Item	Specification
Standard functions	Input frequency resolution	Digital setting: 0.01 Hz Analog setting: Max. frequency x 0.025%
	Control mode	Voltage/Frequency (V/F) control
	Torque boost	Automatic boost; customized boost 0.1 % to 30.0 %
	V/F curve	Linear V/F curve Multi-point V/F curve Complete V/F separation Half V/F separation
	Ramp mode	Straight-line ramp S-curve ramp Four separate acceleration/deceleration time settings in the range of 0.0s to 6500.0s
	DC injection braking	Braking frequency: 0 Hz to max. frequency Active time: 0.0s to 36.0s. Current level: 0.0% to 100.0%.
	Jog running	Frequency range: 0.00 to max. frequency Acceleration/Deceleration time:0.0s to 6500.0s
	Simple PLC, multiple preset speeds	The system implements up to 16 speeds by using simple PLC function or by using digital input signals.
	Onboard PID	The system implements the Proportional-Integral-Derivative (PID) function in the closed-loop control.
	Automatic voltage regulation (AVR)	The system maintains a constant output voltage automatically when the grid voltage changes through the permissible range.
	Overtorque and overcurrent stall control	The system limits the output current and voltage automatically during operation to prevent frequent or excessive trips.
	Overcurrent fast prevention	The function helps to avoid frequent overcurrent faults.
	Current limit and control	The system limits the output current automatically during operation to prevent frequent or excessive trips.
Individualized Functions	Power dip ride-through	Load feedback energy compensates for any voltage reduction, allowing the AC drive to continue to operate for a short time during power dips.
	Overcurrent fast prevention	The function helps to avoid frequent overcurrent faults.
	Virtual I/O	Five groups of virtual digital inputs/outputs (DIs/DOs) support simple logic control.
	Timing control	Time range: 0.0 to 6500.0 minutes
	Dual-motor switchover	The AC drive has two groups of motor parameters and can control up to two motors.
	Multiple field buses	The drive supports four field buses: Modbus, PROFIBUS-DP, CANlink, and CANopen.
	Motor overheat protection	Optional extension I/O card 1. Option: The optional I/O extension card allows AI3 to receive a signal from the motor temperature sensor input (PT100, PT1000) to implement motor overheat protection.
	User programmable function	Option: The optional programming card supports secondary development in a programming environment compatible with the Inovance programmable logic controller (PLC).
	Advanced software tool	Software in the AC drive allows users to configure some operating parameters, and provides a virtual oscilloscope display that shows system status.

Item		Specification
RUN	Running command	Allows different methods of switching between running commands: <ul style="list-style-type: none"> <li>◆ Operating panel (keypad &amp; display)</li> <li>◆ Terminal I/O control</li> <li>◆ Serial communication</li> </ul>
	Main frequency reference setting channel	Supports up to 10 frequency reference setting channels and allows different methods of switching between frequency reference setting channels: <ul style="list-style-type: none"> <li>◆ Digital setting</li> <li>◆ Analog voltage reference</li> <li>◆ Analog current reference</li> <li>◆ Pulse reference</li> <li>◆ Communication reference</li> </ul>
	Auxiliary frequency reference setting channel	Supports up to 10 auxiliary frequency sources, and allows fine tuning of the auxiliary frequency and main & auxiliary calculation.
	Input terminals	Standard: <ul style="list-style-type: none"> <li>◆ Five digital input (DI) terminals, one of which supports up to 100 kHz high-speed pulse inputs.</li> <li>◆ Two analog input (AI) terminals, one of which supports only 0 to 10 V input, and the other supports 0 to 10 V and 0 to 20 mA current input.</li> </ul> Expanded capacity: <ul style="list-style-type: none"> <li>◆ Five digital input (DI) terminals.</li> <li>◆ One AI terminal that supports -10 to +10 V voltage input and PT100/PT1000 motor temperature sensor inputs.</li> </ul>
Display and operating panel	Output terminals	Standard: <ul style="list-style-type: none"> <li>◆ Single high-speed pulse output terminal (open-collector) for square-wave signal output in the frequency range 0 to 100 kHz</li> <li>◆ Single digital output (DO) terminal</li> <li>◆ Single relay output terminal</li> <li>◆ Single analog output (AO) terminal that supports either a current output in the range 0 to 20 mA or a voltage output in the range 0 to 10 V.</li> </ul> Expanded capacity: <ul style="list-style-type: none"> <li>◆ Single digital output (DO) terminal</li> <li>◆ Single relay output terminal</li> <li>◆ Single analog output (AO) terminal that supports either a current output in the range 0 to 20 mA or a voltage output in the range 0 to 10 V.</li> </ul>
	LED display	It shows parameter values.
	LCD display	It is optional and shows parameters in Chinese or English.
	Parameter copy	The LCD operating panel can be used to copy parameters quickly.
	Key locking and function	Keys on the control panel can be locked or partially locked electronically to prevent accidental operation.

## 1 Product Information

	Item	Specification
Protections	Phase loss protection	Input phase loss protection Output phase loss protection
	Instantaneous overcurrent protection	The AC drive stops when 250% of rated output current is exceeded.
	Overtoltage protection	The AC drive stops when the DC bus voltage of the main circuit is above 820 V.
	Undervoltage protection	The AC drive stops when the DC bus voltage of the main circuit is below 350 V.
	Overheat protection	Protection is triggered when the AC Drive bridge gets overheated.
	Overload protection	The AC drive stops after running at 130% of rated current for 60 seconds.
	Overcurrent protection	The AC drive stops when 2.5 times of rated current of the AC drive is exceeded.
	Braking protection	Braking unit overload protection Braking resistor short-circuit protection
	Short-circuit protection	Output phase-to-phase short-circuit protection Output phase-to-ground short-circuit protection
Environment	Installation location	Install the AC Drive where it is indoors and protected from direct sunlight, dust, corrosive or combustible gases, oil smoke, vapor, ingress from water or any other liquid, and salt.
	Altitude	Below 1000 m If the altitude exceeds 1000 m, de-rating by 1% for per 100 m increase Max. 3000 m (Note: The maximum altitude for 0.4 to 3 kW AC drives is 2000 m. For use at altitude over 2000 m, contact Inovance.)
	Ambient temperature:	-10° C to +40° C. If the ambient temperature is not in this range, de-rating by 1.5% per 1° C increase Max. temperature: 50° C
	Humidity	Less than 95% RH non-condensing
	Vibration	Less than 9.8 m/s <sup>2</sup> (1G)
	Storage temperature	-20° C to +60° C
	Pollution degree	PD2
	Overtoltage category	OVCIII

## 1.4 Overall Dimensions

### 1.4.1 Overall Dimensions of MD290T0.4G/0.7PB to MD290T160G/200P and MD290-2T0.4G/0.7PB to MD290-2T55G/75P




Figure 1-4 Overall and mounting dimensions of MD290T0.4G/0.7PB to MD290T37G/45P(B) and MD290-2T0.4G/0.7PB to MD290-2T18.5G/22P(B)




Figure 1-5 Overall and mounting dimensions of MD290T45G/55P(B) to MD290T160G/200P and MD290-2T22G/30P(B) to MD290-2T55G/75P

1 Product Information

Table 1-6 Mounting hole dimensions of MD290T0.4G/0.7PB to MD290T160G/200P

AC Drive Model	Hole Dimensions (mm)		Overall Dimensions (mm)				Hole Diameter (mm)	Weight (kg)
	A	B	H	H1	W	D	d	
MD290T0.4G/0.7PB	119	189	200	-	130	152	Ø5	1.6
MD290T0.7G/1.1PB								
MD290T1.1G/1.5PB								
MD290T1.5G/2.2PB								
MD290T2.2G/3.0PB								
MD290T3.0G/3.7PB	119	189	200	-	130	162	Ø5	2.0
MD290T3.7G/5.5PB								
MD290T5.5G/7.5PB	128	238	250	-	140	170	Ø6	3.3
MD290T7.5G/11PB								
MD290T11G/15PB	166	266	280	-	180	170	Ø6	4.3
MD290T15G/18.5PB								
MD290T18.5G/22P(B)	195	335	350	-	210	192	Ø6	7.6
MD290T22G/30P(B)								
MD290T18.5G/22P(B)-T	195	335	350	-	210	192	Ø6	10.0
MD290T22G/30P(B)-T								
MD290T30G/37P(B)	230	380	400	-	250	220	Ø7	17.5
MD290T37G/45P(B)								
MD290T45G/55P(B)	245	523	525	542	300	275	Ø10	35.0
MD290T55G/75P(B)								
MD290T75G/90P(B)	270	560	554	580	338	315	Ø10	51.5
MD290T90G/110P								
MD290T110G/132P								
MD290T132G/160P	320	890	874	915	400	320	Ø10	85.0
MD290T160G/200P								

Table 1-7 Mounting hole dimensions of MD290-2T0.4G/0.7PB to MD290-2T55G/75P

AC Drive Model	Hole Dimensions (mm)		Overall Dimensions (mm)				Hole Diameter (mm)	Weight (kg)
	A	B	H	H1	W	D	d	
MD290-2T0.4G/0.7PB	119	189	200	-	130	152	Ø5	1.6
MD290-2T0.7G/1.1PB								
MD290-2T1.1G/1.5PB								
MD290-2T1.5G/2.2PB								
MD290-2T2.2G/3.7PB	119	189	200	-	130	162	Ø5	2.0
MD290-2T3.7G/5.5PB								
MD290-2T5.5G/7.5PB	128	238	250	-	140	170	Ø6	3.3
MD290-2T7.5G/11PB								
MD290-2T11G/15P(B)	166	266	280	-	180	170	Ø6	4.3
MD290-2T15G/18.5P(B)								
MD290-2T18.5G/22P(B)	195	335	350	-	210	192	Ø6	7.6
MD290-2T22G/30P(B)								
MD290-2T30G/37P(B)	230	380	400	-	250	220	Ø7	17.5
MD290-2T37G/45P(B)								
MD290-2T45G/55P(B)	245	523	525	542	300	275	Ø10	35.0
MD290-2T55G/75P								
MD290-2T75G/90P(B)	270	560	554	580	338	315	Ø10	51.5
MD290-2T90G/110P								
MD290-2T110G/132P								

### 1.4.2 Overall Dimensions of MD290T200G to MD290T450G and MD290T220P to MD290T500P




Figure 1-6 Overall and mounting dimensions of MD290T200G to MD290T450G and MD290T220P to MD290T500P

Table 1-8 Mounting hole dimensions of MD290T200G to MD290T450G and MD290T220P to MD290T500P

AC Drive Model		Hole Dimensions (mm)				Overall Dimensions (mm)					Hole Diameter (mm)	Weight (kg)
		A1	A2	B1	B2	H	H1	W	W1	D		
MD290T200G	MD290T220P	240	150	1035	86	1086	1134	300	360	500	Ø13	110
-	MD290T250P											
MD290T220G	MD290T280P	225	185	1175	97	1248	1284	330	390	545	Ø13	155
MD290T250G	MD290T315P											
MD290T280G	MD290T355P	240	200	1280	101	1355	1405	340	400	545	Ø16	185
MD290T315G	MD290T400P											
MD290T355G	MD290T450P											
MD290T400G	MD290T500P											
MD290T450G	-											

### 1.4.3 Overall Dimensions of MD290T200G-L to MD290T450G-L and MD290T220P-L to MD290T500P-L




Figure 1-7 Overall and mounting dimensions of MD290T200G-L to MD290T450G-L and MD290T220P-L to MD290T500P-L

Table 1-9 Mounting hole dimensions of MD290T200G-L to MD290T450G-L and MD290T220P-L to MD290T500P-L (with the reactor base)

AC Drive Model		Hole Dimensions (mm)				Overall Dimensions (mm)					Hole Diameter (mm) D1	Weight (kg)
		A1	A2	B1	B2	H	H1	W	W1	D		
MD290T200G-L	MD290T220P-L	240	150	1035	424	1424	1472	300	360	500	Ø13	160
-	MD290T250P-L											
MD290T220G-L	MD290T280P-L	225	185	1175	435	1586	1622	330	390	545	Ø13	215
MD290T250G-L	MD290T315P-L											
MD290T280G-L	MD290T355P-L	240	200	1280	432	1683	1733	340	400	545	Ø16	245
MD290T315G-L	MD290T400P-L											
MD290T355G-L	MD290T450P-L											
MD290T400G-L	MD290T500P-L											
MD290T450G-L	-											

## 2 System Connections

### 2.1 Connection Diagram

When using the AC drive to drive an asynchronous motor, a variety of electrical devices must be installed on both input and output sides to ensure system safety and stability. The following figure shows how to configure the AC drive to operate with the peripheral devices.




Figure 2-1 MD290 series system composition



- ◆ The preceding figure is just a schematic system connection diagram of the MD290 series AC drive. For peripherals and options, see 19010321 MD290 Series AC Drive Advanced User Guide.

## 2.2 System Structure

Table 2-1 Description of peripheral electrical devices in the MD290 series AC drive system

Device	Mounting Location	Function Description
Breaker	Between the power supply and AC drive input side	MCCB: Cuts off power supply when overcurrent occurs on downstream devices. Leakage breaker: Provides protection against potential leakage current during AC drive running to prevent electric shock and even a fire.
Fuse	Between the power supply and AC drive input side	Provides protection in case of short circuit.
(Electromagnetic) Contactor	Between the breaker and AC drive input side	Switches ON/OFF the AC drive. Do not start/stop the AC drive frequently by switching the contactor ON/OFF (time interval is at least one hour) nor use it to directly start the AC drive.
Input reactor	AC drive input side	Improves the power factor of power input side. Eliminates higher harmonics of the input side effectively and prevents other devices from being damaged due to distortion of voltage waveform. Eliminates input current unbalance caused by inter-phase unbalance.
EMC filter	AC drive input side	Reduces external conduction and radiation interference of the AC drive. Decreases conduction interference flowing from power supply to the AC drive and improve the anti-interference capacity of the AC drive.
DC reactor	Standard configuration for the AC drive of 30G/37P and above and optional for the AC drive of 18.5G/22P to 22G/30P	Improves the power factor of power input side. Improves efficiency and thermal stability of the AC drive. Eliminates impact of higher harmonics of the AC drive input side and reduces external conduction and radiation interference.
Braking resistor	GB-type models of 75G/90P and below	Use a braking resistor for the GB-type models of 75G/90P and below. Dissipates regenerative energy during motor deceleration.
Braking unit	Full series except the GB-type models	Use Inovance's braking unit MDBUN and MDBU and recommended braking resistor for full series except the GB-type model. Dissipates regenerative energy during motor deceleration.

Device	Mounting Location	Function Description
Output reactor	Between the AC drive output side and the motor, close to the AC drive	The output side of the AC drive generally has much higher harmonics. When the motor is far from the AC drive, there is much distributed capacitance in the circuit and certain harmonics may cause resonance in the circuit, which will: <ol style="list-style-type: none"> <li>1) Degrade motor insulation performance and damage the motor in long run.</li> <li>2) Generate large leakage current and cause frequent AC drive protection trips.</li> </ol> If the distance between the AC drive and the motor is greater than 100 m, it is recommended that an AC output reactor be installed.
dv/dt reactor	AC drive output side, close to the AC drive	Optional. Protects motor insulation and reduces bearing current.
Output magnetic ring	AC drive output side, close to the AC drive	Reduces bearing current.
Motor	AC drive output side	Select an appropriate motor.

**NOTE**

- ◆ Do not install a capacitor or surge protection device (SPD) on the output side of AC drive. Otherwise, the AC drive, capacitor, or SPD may be damaged.
- ◆ Inputs/Outputs (main circuit) of the AC drive contain harmonics, which may interfere with the communication device connected to the AC drive. Therefore, install an anti-interference filter to minimize interference.

## 2.3 Options

Peripherals and options include braking units, function extension cards, and external operating panel, as listed in the following table. For use of each option, see its user guide. If you need to purchase the following options, specify the required option in the order.

Table 2-2 Options

Name	Model	Description	Remarks
Built-in braking unit	Marked by "B"	Three phase 380–480 V models: optional for 0.4–75 kW G-type models and 0.7–90 kW P-type models Three phase 200–240 V models: optional for 0.4–37 kW G-type models and 0.7–45 kW P-type models	-
External braking unit	MDBUN and MDBU	Three phase 380–480 V models: G-type models of 90 kW and above and P-type models of 110 kW and above Three phase 200–240 V models: G-type models of 45 kW and above and P-type models of 55 kW and above	Multiple braking units are connected in parallel.
I/O extension card 1	MD38IO1	Provides: <ul style="list-style-type: none"> <li>◆ Five extra DI terminals</li> <li>◆ An analog input (AI3) terminal</li> <li>◆ A relay output terminal</li> <li>◆ A digital output terminal</li> <li>◆ An analog output terminal</li> </ul> MODBUS/CANlink supported Can be connected to PT100 and PT1000.	Available for models of 15 kW and above
I/O extension card 2	MD38IO2	Provides three extra DI terminals.	Available for all models
I/O extension card 3	MD38IO3	Provides: <ul style="list-style-type: none"> <li>◆ Three extra DI terminals</li> <li>◆ One RS-485 communication signal isolation input terminal</li> <li>◆ One NO relay output terminal</li> </ul>	Available for all models
RS-485 communication card	MD38TX1	Provides the isolated Modbus communication adapter card.	Available for all models
CANlink communication card	MD38CAN1	CANlink communication adapter card	Available for all models
CANopen communication card	MD38CAN2	CANopen communication adapter card	Available for all models

Name	Model	Description	Remarks
Profibus-DP communication card	MD38DP2	Profibus-DP communication card	Available for models of 15 kW or above
PROFINET communication extension card	MD500-PN1	PROFINET communication adapter card	Available for all models
User programmable card	MD38PC1	User programmable extension card Compatible with H1U-series PLCs of Inovance	Available for models of 15 kW or above
External LCD operating panel	MDKE9	External LCD display and operating panel	Parameter copy and download supported
External LED operating panel	MD32NKE1	Connected to the external LED operating panel through the RJ45 interface	Available for the MD series
Mounting base of the MDKE9 operating panel	CP600-BASE1	-	-
Through-hole mounting bracket	MD500-AZJ-A1T*	Used to mount the AC drive to the middle of the cabinet	Each model has its own bracket. For details, see <a href="#">"Table 3-1 Through-hole mounting bracket models (three phase 380–480 V)"</a> .
Guide rail	MD500-AZJ-A3T10	For MD290T200G(-L) to MD290T450G(-L) and MD290T220P(-L) to MD290T500P(-L), it is recommended that a guide rail be used to push the AC drive into the cabinet.	For details, see the guide rail installation guide in the package.
External operating panel cable	MDCAB	Standard: 8 cores Can be connected to MD32NKE1, MD32KC, and MDCP	Standard length: 3 m
Cable support bracket	MD500-AZJ-A2T*	Used for secondary fixing of power cables and stable grounding of the shield	For details, see 19010321 MD290 Series AC Drive Advanced User Guide.

## 2.4 Selection of Cables, Breakers, and Contactors

Table 2-3 Selection of cables, breakers, and contactors (three-phase 380–480 V)

Model	RST/UVW		Ground Cable		Terminal Width of the AC Drive (mm)	Screw	Recommended Fuse Busmann Passed UL Certification		Recommended Contactor	Recommended Breaker
	Recommended Cable (mm <sup>2</sup> ) <sup>[1]</sup>	Recommended Lug Model	Recommended Cable (mm <sup>2</sup> ) <sup>[1]</sup>	Recommended Lug Model			Rated Current (A)	Model		
Three-phase 380–480 V, 50/60 Hz										
MD290T0.4G/0.7PB	3 x 0.75	TNR0.75-4	0.75	TNR5.5-5	10.2	M4	5	FWP-5B	9	4
MD290T0.7G/1.1PB	3 x 0.75	TNR0.75-4	0.75	TNR8-5	10.2	M4	10	FWP-10B	9	6
MD290T1.1G/1.5PB	3 x 0.75	TNR0.75-4	0.75	TNR5.5-5	10.2	M4	10	FWP-10B	9	6
MD290T1.5G/2.2PB	3 x 0.75	TNR0.75-4	0.75	TNR8-5	10.2	M4	10	FWP-10B	9	10
MD290T2.2G/3.0PB	3 x 0.75	TNR0.75-4	0.75	TNR5.5-5	10.2	M4	15	FWP-15B	12	13
MD290T3.0G/3.7PB	3 x 1.5	TNR1.25-4	1.5	TNR8-5	10.2	M4	20	FWP-20B	16	16
MD290T3.7G/5.5PB	3 x 2.5	TNR2-4	2.5	TNR5.5-5	10.2	M4	30	FWP-30B	26	25
MD290T5.5G/7.5PB	3 x 4	TNR3.5-5	4	TNR8-5	10.2	M5	40	FWP-40B	26	32
MD290T7.5G/11PB	3 x 6	TNR5.5-5	6	TNR5.5-5	13.0	M5	60	FWP-60B	38	50
MD290T11G/15PB	3 x 10	TNR8-5	10	TNR8-5	13.0	M5	70	FWP-70B	50	63
MD290T15G/18.5PB	3 x 10	TNR8-5	10	TNR8-5	14.3	M5	70	FWH-70B	50	63
MD290T18.5G/22P(B)	3 x 16	GTNR16-6	16	GTNR16-6	15.0	M6	100	FWH-100B	65	80
MD290T22G/30P(B)	3 x 16	GTNR16-6	16	GTNR16-6	15.0	M6	125	FWH-125B	80	80
MD290T30G/37P(B)	3 x 25	GTNR25-6	16	GTNR16-6	18.0	M6	125	FWH-125B	80	100
MD290T37G/45P(B)	3 x 35	GTNR35-6	16	GTNR16-6	18.0	M6	150	FWH-150B	95	160
MD290T45G/55P(B)	3 x 50	GTNR50-8	25	GTNR25-8	26.8	M8	200	FWH-200B	115	160
MD290T55G/75P(B)	3 x 70	GTNR70-8	35	GTNR35-8	26.8	M8	250	FWH-250A	150	250
MD290T75G/90P(B)	3 x 95	GTNR95-12	50	GTNR50-12	30.6	M12	275	FWH-275A	170	250
MD290T90G/110P	3 x 120	GTNR120-12	70	GTNR70-12	30.6	M12	325	FWH-325A	205	250
MD290T110G/132P	3 x 150	GTNR150-12	95	GTNR95-12	30.6	M12	400	FWH-400A	245	400
MD290T132G/160P	3 x 185	BC185-12	95	BC95-12		M12	500	FWH-500A	300	400
MD290T160G/200P	2 x (3 x 95)	BC95-12	95	BC95-12		M12	600	FWH-600A	410	500
MD290T200G(-L)	2 x (3 x 95)	BC95-12	95	BC95-12	*	M12	600	FWH-600A	410	500
MD290T220P(-L)	2 x (3 x 120)	BC120-12	120	BC120-12		M12	700	FWH-700A	410	630
MD290T220G(-L)	2 x (3 x 120)	BC120-12	120	BC120-12	*	M12	700	FWH-700A	410	630
MD290T250P(-L)	2 x (3 x 120)	BC120-12	120	BC120-12		M12	800	FWH-800A	475	630
MD290T250G(-L)	2 x (3 x 120)	BC120-12	120	BC120-12	*	M12	800	FWH-800A	475	630
MD290T280P(-L)	2 x (3 x 150)	BC150-12	150	BC150-12		M12	800	FWH-800A	620	800
MD290T280G(-L)	2 x (3 x 150)	BC150-12	150	BC150-12	*	M12	800	FWH-800A	620	800
MD290T315P(-L)	2 x (3 x 185)	BC185-16	185	BC185-16		M16	1000	170M5016	620	800
MD290T315G(-L)	2 x (3 x 185)	BC185-16	185	BC185-16	*	M16	1000	170M5016	620	800
MD290T355P(-L)	2 x (3 x 185)	BC185-16	185	BC185-16		M16	1000	170M5016	620	800
MD290T355G(-L)	2 x (3 x 185)	BC185-16	185	BC185-16	*	M16	1000	170M5016	620	800
MD290T400P(-L)	2 x (3 x 240)	BC240-16	240	BC240-16		M16	1400	170M6017	800	1000
MD290T400G(-L)	2 x (3 x 240)	BC240-16	240	BC240-16	*	M16	1400	170M6017	800	1000

Model	RST/UVW		Ground Cable		Terminal Width of the AC Drive (mm)	Screw	Recommended Fuse Bussmann Passed UL Certification		Recommended Contactor	Recommended Breaker
	Recommended Cable (mm <sup>2</sup> ) <sup>[1]</sup>	Recommended Lug Model	Recommended Cable (mm <sup>2</sup> ) <sup>[1]</sup>	Recommended Lug Model			Rated Current (A)	Model		
MD290T450P(-L)	2 x (3 x 240)	BC240-16	240	BC240-16		M16	1400	170M6017	800	1000
MD290T450G(-L)	2 x (3 x 240)	BC240-16	240	BC240-16	*	M16	1400	170M6017	800	1000
MD290T500P(-L)	2 x (3 x 300)	BC300-16	300	BC300-16		M16	1400	170M6017	1000	1250

Table 2-4 Cable selection (three-phase 380–480 V) (with UL certification)

Model	RST/UVW		Ground Cable		Terminal Width of the AC Drive (mm)	Screw
	Recommended Cable (AWG/mil) <sup>[2]</sup>	Recommended Lug Model	Recommended Cable (AWG/kcmil) <sup>[2]</sup>	Recommended Lug Model		
Three-phase 380–480 V, 50/60 Hz						
MD290T0.4G/0.7PB	14	TLK2.5-4	2×14	TLK2.5-4	10.2	M4
MD290T0.7G/1.1PB	14	TLK2.5-4	2×14	TLK2.5-4	10.2	M4
MD290T1.1G/1.5PB	14	TLK2.5-4	2×14	TLK2.5-4	10.2	M4
MD290T1.5G/2.2PB	14	TLK2.5-4	2×14	TLK2.5-4	10.2	M4
MD290T2.2G/3.0PB	14	TLK2.5-4	2×14	TLK2.5-4	10.2	M4
MD290T3.0G/3.7PB	14	TLK2.5-4	2×14	TLK2.5-4	10.2	M4
MD290T3.7G/5.5PB	10	TLK6-4	2×10	TLK6-4	10.2	M4
MD290T5.5G/7.5PB	10	TLK6-5	2×10	TLK6-5	10.2	M5
MD290T7.5G/11PB	8	TLK10-5	2×8	TLK10-5	13	M5
MD290T11G/15PB	6	TLK16-5	6	TLK16-5	13	M5
MD290T15G/18.5PB	6	TLK16-5	6	TLK16-5	14.3	M5
MD290T18.5G/22P(B)	4	TLK25-6	4	TLK25-6	15	M6
MD290T22G/30P(B)	4	TLK25-6	4	TLK25-6	15	M6
MD290T30G/37P(B)	3	TLK35-6	4	TLK25-6	18	M6
MD290T37G/45P(B)	2	TLK35-6	4	TLK25-6	18	M6
MD290T45G/55P(B)	1/0	TLK50-8	3	TLK35-8	26.8	M8
MD290T55G/75P(B)	3/0	TLK95-10	1	TLK50-8	26.8	M8
MD290T75G/90P(B)	4/0	TLK120-12	1/0	TLK70-12	30.6	M12
MD290T90G/110P	300	SQNBS180-12	3/0	TLK95-12	30.6	M12
MD290T110G/132P	400	SQNBS250-12	4/0	TLK120-12	30.6	M12
MD290T132G/160P	500	SQNBS250-12	250	TLK300-12		M12
MD290T160G/200P	2×250	SQNBS150-12	250	SQNBS150-12		M12
MD290T200G(-L)	2×250	TLK150-12	250	TLK150-12	*	M12
MD290T220P(-L)	2×300	TLK185-12	300	TLK185-12		M12
MD290T220G(-L)	2×300	TLK185-12	300	TLK185-12	*	M12
MD290T250P(-L)	2×350	TLK185-12	350	TLK185-12		M12
MD290T250G(-L)	2×350	TLK185-12	350	TLK185-12		M12
MD290T280P(-L)	2×350	TLK185-12	350	TLK185-12	*	M12
MD290T280G(-L)	2×400	TLK185-12	400	TLK185-12	*	M12

## 2 System Connections

Model	RST/UVW		Ground Cable		Terminal Width of the AC Drive (mm)	Screw
	Recommended Cable (AWG/mil) <sup>[2]</sup>	Recommended Lug Model	Recommended Cable (AWG/kcmil) <sup>[2]</sup>	Recommended Lug Model		
MD290T315P(-L)	2×500	SQNBS325-16	500	SQNBS325-16		M16
MD290T315G(-L)	2×600	SQNBS325-16	600	SQNBS325-16		M16
MD290T355P(-L)	2×500	TLK300-16	500	TLK300-16	*	M16
MD290T355G(-L)	2×600	TLK400-16	600	TLK400-16	*	M16
MD290T400P(-L)	2×700	TLK400-16	700	TLK400-16		M16
MD290T400G(-L)	2×700	TLK400-16	700	TLK400-16	*	M16
MD290T450P(-L)	4×300	TLK185-16	2×300	TLK185-16		M16
MD290T450G(-L)	4×300	TLK185-16	2×300	TLK185-16	*	M16
MD290T500P(-L)	4×300	TLK185-16	2×300	TLK185-16		M16

Table 2-5 Selection of cables, breakers, and contactors (three-phase 200–240 V)

Model	RST/UVW		Ground Cable		Terminal Width of the AC Drive (mm)	Screw	Recommended Fuse Bussmann Passed UL Certification		Recom- mended Contactor	Recom- mended Breaker
	Recom- mended Cable (mm <sup>2</sup> ) <sup>[1]</sup>	Recom- mended Lug Model	Recom- mended Cable (mm <sup>2</sup> ) <sup>[1]</sup>	Recom- mended Lug Model			Rated Current (A)	Model	Rated Current (A)	Rated Current (A)
Three-phase 200–240 V, 50/60 Hz										
MD290-2T0.4G/0.7PB	3×0.75	TNR0.75-4	0.75	TNR8-5	10.2	M4	10	FWP-10B	9	6
MD290-2T0.7G/1.1PB	3×0.75	TNR0.75-4	0.75	TNR8-5	10.2	M4	10	FWP-10B	9	10
MD290-2T1.1G/1.5PB	3×0.75	TNR0.75-4	0.75	TNR5.5-5	10.2	M4	15	FWP-15B	12	13
MD290-2T1.5G/2.2PB	3×1.5	TNR1.25-4	1.5	TNR8-5	10.2	M4	20	FWP-20B	16	16
MD290-2T2.2G/3.7PB	3×2.5	TNR2-4	2.5	TNR5.5-5	10.2	M4	30	FWP-30B	26	25
MD290-2T3.7G/5.5PB	3×4	TNR3.5-5	4	TNR8-5	10.2	M5	40	FWP-40B	26	32
MD290-2T5.5G/7.5PB	3×10	TNR8-5	10	TNR8-5	13.0	M5	70	FWP-70B	50	63
MD290-2T7.5G/11PB	3×10	TNR8-5	10	TNR8-5	14.3	M5	70	FWH-70B	50	63
MD290-2T11G/15P(B)	3×16	GTNR16-6	16	GTNR16-6	15.0	M6	125	FWH-125B	80	80
MD290-2T15G/18.5P(B)	3×25	GTNR25-6	16	GTNR16-6	18.0	M6	125	FWH-125B	80	100
MD290-2T18.5G/22P(B)	3×35	GTNR35-6	16	GTNR16-6	18.0	M6	150	FWH-150B	95	160
MD290-2T22G/30P(B)	3×50	GTNR50-8	25	GTNR25-8	26.8	M8	200	FWH-200B	115	160
MD290-2T30G/37P(B)	3×70	GTNR70-8	35	GTNR35-8	26.8	M8	250	FWH-250A	150	250
MD290-2T37G/45P(B)	3×95	GTNR95-12	50	GTNR50-12	30.6	M12	275	FWH-275A	170	250
MD290-2T45G/55P	3×120	GTNR120-12	70	GTNR70-12	30.6	M12	325	FWH-325A	205	250
MD290-2T55G/75P	3×150	GTNR150-12	95	GTNR95-12	30.6	M12	400	FWH-400A	245	400

[1] Suitable for the Chinese standard. "3 × 10" indicates one three-conductor cable, and "2 × (3 × 95)" indicates two three-conductor cables.

[2] Suitable for the American standard. "5" indicates 5AWG, "1/0" indicates 0AWG, "2/0" indicates 00AWG, "3/0" indicates 000AWG, "4/0" indicates 0000AWG, and "2 × 250" indicates two 250 kcmil cables.



### NOTE

The preceding recommended lugs are the TNR, GTNR, and BC series lugs of Suzhou Yuanli. The lugs with UL certifications are KST's TLK and SQNBS series lugs.

## 2.5 Selection of the AC Output Reactor

Whether to install an AC output reactor on the output side of the AC drive is dependent on actual situations. The cable connecting the AC drive and motor cannot be too long. Otherwise, capacitance enlarges and thus high-harmonics current may be easily generated. To avoid these problems, install an AC output reactor close to the AC drive if the cable length is equal to or larger than the values listed in the following table.

Table 2-6 Cable length limit with the output reactor configured (three phase 380–480 V)

AC Drive Power (kW)	Rated Voltage (V)	Minimum Cable Length with Output Reactor Configured (m)	AC Drive Power (kW)	Rated Voltage (V)	Minimum Cable Length with Output Reactor Configured (m)
0.4–4	200–500	50	15	200–500	125
5.5	200–500	70	18.5	200–500	135
7.5	200–500	100	≥ 22	200–500	150
11	200–500	110			

Table 2-7 Cable length limit with the output reactor configured (three phase 200–240 V)

AC Drive Power (kW)	Rated Voltage (V)	Minimum Cable Length with Output Reactor Configured (m)	AC Drive Power (kW)	Rated Voltage (V)	Minimum Cable Length with Output Reactor Configured (m)
0.4–3.7	200–500	50	7.5	200–500	125
3.7	200–500	70	≥ 11	200–500	150
5.5	200–500	110			

Table 2-8 Recommended models of the AC output reactor (three phase 380–480 V)

AC Drive Model	AC Output Reactor Model (Inovance)	AC Drive Model	AC Output Reactor Model (Inovance)
MD290T0.4G/0.7PB	MD-OCL-5-1.4-4T-1%	MD290T18.5G/22P(B)	MD-OCL-50-0.14-4T-1%
MD290T0.7G/1.1PB	MD-OCL-5-1.4-4T-1%	MD290T22G/30P(B)	MD-OCL-60-0.12-4T-1%
MD290T1.1G/1.5PB	MD-OCL-5-1.4-4T-1%	MD290T30G/37P(B)	MD-OCL-80-0.087-4T-1%
MD290T1.5G/2.2PB	MD-OCL-7-1.0-4T-1%	MD290T37G/45P(B)	MD-OCL-120-0.058-4T-1%
MD290T2.2G/3.0PB	MD-OCL-10-0.7-4T-1%	MD290T45G/55P(B)	MD-OCL-120-0.058-4T-1%
MD290T3.0G/3.7PB	MD-OCL-10-0.7-4T-1%	MD290T55G/75P(B)	MD-OCL-150-0.047-4T-1%
MD290T3.7G/5.5PB	MD-OCL-15-0.47-4T-1%	MD290T75G/90P(B)	MD-OCL-200-0.035-4T-1%
MD290T5.5G/7.5PB	MD-OCL-20-0.35-4T-1%	MD290T90G/110P	MD-OCL-250-0.028-4T-1%
MD290T7.5G/11PB	MD-OCL-30-0.23-4T-1%	MD290T110G/132P	MD-OCL-330-0.021-4T-1%
MD290T11G/15PB	MD-OCL-40-0.18-4T-1%	MD290T132G/160P	MD-OCL-330-0.021-4T-1%
MD290T15G/18.5PB	MD-OCL-40-0.18-4T-1%	MD290T160G/200P	MD-OCL-490-0.014-4T-1%

Table 2-9 Recommended models of the AC output reactor (three phase 200–240 V)

AC Drive Model	AC Output Reactor Model (Inovance)	AC Drive Model	AC Output Reactor Model (Inovance)
MD290-2T0.4G/0.7PB	MD-OCL-5-1.4-4T-1%	MD290-2T11G/15P(B)	MD-OCL-60-0.12-4T-1%
MD290-2T0.7G/1.1PB	MD-OCL-7-1.0-4T-1%	MD290-2T15G/18.5P(B)	MD-OCL-80-0.087-4T-1%
MD290-2T1.1G/1.5PB	MD-OCL-10-0.7-4T-1%	MD290-2T18.5G/22P(B)	MD-OCL-120-0.058-4T-1%

## 2 System Connections

AC Drive Model	AC Output Reactor Model (Inovance)	AC Drive Model	AC Output Reactor Model (Inovance)
MD290-2T1.5G/2.2PB	MD-OCL-10-0.7-4T-1%	MD290-2T22G/30P(B)	MD-OCL-120-0.058-4T-1%
MD290-2T2.2G/3.7PB	MD-OCL-15-0.47-4T-1%	MD290-2T30G/37P(B)	MD-OCL-150-0.047-4T-1%
MD290-2T3.7G/5.5PB	MD-OCL-20-0.35-4T-1%	MD290-2T37G/45P(B)	MD-OCL-200-0.035-4T-1%
MD290-2T5.5G/7.5PB	MD-OCL-40-0.18-4T-1%	MD290-2T45G/55P	MD-OCL-250-0.028-4T-1%
MD290-2T7.5G/11PB	MD-OCL-40-0.18-4T-1%	MD290-2T55G/75P	MD-OCL-330-0.021-4T-1%



### NOTE

- ◆ Use AC output reactors of MD290T200G-L to MD290T450G-L for AC drives MD290T200G to MD290T450G.
- ◆ Use AC output reactors of MD290T220P-L to MD290T500P-L for AC drives MD290T220P to MD290T500P.

## 2.6 Selection of Braking Components

Table 2-10 Braking component selection (three phase 380–480 V)

AC Drive Model	Applicable Motor (kW)	Braking Unit		125% Braking Torque (10% ED, Max. 10s)		Remarks	Minimum Braking Resistance (Ω)			
		Model	QTY	Recommended Braking Resistor	QTY					
MD290T0.4G/0.7PB	0.75	Built-in		140 W 800 Ω	1	AC drive models ending with letter "B"	96			
MD290T0.7G/1.1PB	1.1			220 W 500 Ω	1		96			
MD290T1.1G/1.5PB	1.5			300 W 380 Ω	1		96			
MD290T1.5G/2.2PB	2.2			440 W 260 Ω	1		96			
MD290T2.2G/3.0PB	3.0			600 W 190 Ω	1		64			
MD290T3.0G/3.7PB	3.7			740 W 150 Ω	1		64			
MD290T3.7G/5.5PB	5.5			1100 W 100 Ω	1		32			
MD290T5.5G/7.5PB	7.5			1500 W 75 Ω	1		32			
MD290T7.5G/11PB	11			2200 W 50 Ω	1		32			
MD290T11G/15PB	15			3000 W 38 Ω	1		20			
MD290T15G/18.5PB	18.5			4000 W 32 Ω	1		20			
MD290T18.5G/22P(B)	22			Built-in			4000 W 32 Ω	1	AC drive models ending with letter "B"	24
MD290T22G/30P(B)	30						4500 W 27 Ω	1		24
MD290T30G/37P(B)	37	6000 W 20 Ω	1			19.2				
MD290T37G/45P(B)	45	7000 W 16 Ω	1			14.8				
MD290T45G/55P(B)	55	9000 W 13 Ω	1			12.8				
MD290T55G/75P(B)	75	11000 W 10.5 Ω	1			9.6				
MD290T75G/90P(B)	90	15000 W 7.7 Ω	1			6.8				
MD290T90G/110P	110	MDBUN-60-T	2			9000 W 10.0 Ω	2	Input voltage ≤ 440 VAC		9.3×2
	110	MDBUN-60-5T	2	9000 W 12.8 Ω	2	Input voltage > 440 VAC	10.5×2			
MD290T110G/132P	132	MDBUN-60-T	2	11000 W 9.4 Ω	2	Input voltage ≤ 440 VAC	9.3×2			
	132	MDBUN-60-5T	2	11000 W 10.5 Ω	2	Input voltage > 440 VAC	10.5×2			
MD290T132G/160P	160	MDBUN-90-T	2	13000 W 6.8 Ω	2	Input voltage ≤ 440 VAC	6.2×2			
	160	MDBUN-90-5T	2	13000 W 8.8 Ω	2	Input voltage > 440 VAC	7.0×2			

AC Drive Model	Applicable Motor (kW)	Braking Unit		125% Braking Torque (10% ED, Max. 10s)		Remarks	Minimum Braking Resistance ( $\Omega$ )
		Model	QTY	Recommended Braking Resistor	QTY		
MD290T160G/200P	200	MDBUN-90-T	2	16000 W 6.3 $\Omega$	2	Input voltage $\leq$ 440 VAC	6.2 $\times$ 2
	200	MDBUN-90-5T	2	16000 W 7.2 $\Omega$	2	Input voltage > 440 VAC	7.0 $\times$ 2
MD290T200G	200	MDBU-200-B	2	19000 W 4.5 $\Omega$	2	Input voltage $\leq$ 440 VAC	2.5 $\times$ 2
	200	MDBU-200-C	2	19000 W 5.8 $\Omega$	2	Input voltage > 440 VAC	3.0 $\times$ 2
MD290T220P	220	MDBU-200-B	2	19000 W 4.5 $\Omega$	2	Input voltage $\leq$ 440 VAC	2.5 $\times$ 2
	220	MDBU-200-C	2	19000 W 5.8 $\Omega$	2	Input voltage > 440 VAC	3.0 $\times$ 2
MD290T220G	220	MDBU-200-B	2	21000 W 4.1 $\Omega$	2	Input voltage $\leq$ 440 VAC	2.5 $\times$ 2
	220	MDBU-200-C	2	21000 W 5.3 $\Omega$	2	Input voltage > 440 VAC	3.0 $\times$ 2
MD290T250P	250	MDBU-200-B	2	21000 W 4.1 $\Omega$	2	Input voltage $\leq$ 440 VAC	2.5 $\times$ 2
	250	MDBU-200-C	2	21000 W 5.3 $\Omega$	2	Input voltage > 440 VAC	3.0 $\times$ 2
MD290T250G	250	MDBU-200-B	2	24000 W 3.6 $\Omega$	2	Input voltage $\leq$ 440 VAC	2.5 $\times$ 2
	250	MDBU-200-C	2	24000 W 4.6 $\Omega$	2	Input voltage > 440 VAC	3.0 $\times$ 2
MD290T280P	280	MDBU-200-B	2	27000 W 3.2 $\Omega$	2	Input voltage $\leq$ 440 VAC	2.5 $\times$ 2
	280	MDBU-200-C	2	27000 W 4.1 $\Omega$	2	Input voltage > 440 VAC	3.0 $\times$ 2
MD290T280G	280	MDBU-200-B	2	27000 W 3.2 $\Omega$	2	Input voltage $\leq$ 440 VAC	2.5 $\times$ 2
	280	MDBU-200-C	2	27000 W 4.1 $\Omega$	2	Input voltage > 440 VAC	3.0 $\times$ 2
MD290T315P	315	MDBU-200-B	3	20000 W 4.3 $\Omega$	3	Input voltage $\leq$ 440 VAC	2.5 $\times$ 3
	315	MDBU-200-C	3	20000 W 5.5 $\Omega$	3	Input voltage > 440 VAC	3.0 $\times$ 3
MD290T315G	315	MDBU-200-B	3	20000 W 4.3 $\Omega$	3	Input voltage $\leq$ 440 VAC	2.5 $\times$ 3
	315	MDBU-200-C	3	20000 W 5.5 $\Omega$	3	Input voltage > 440 VAC	3.0 $\times$ 3
MD290T355P	355	MDBU-200-B	3	23000 W 3.8 $\Omega$	3	Input voltage $\leq$ 440 VAC	2.5 $\times$ 3
	355	MDBU-200-C	3	23000 W 4.9 $\Omega$	3	Input voltage > 440 VAC	3.0 $\times$ 3
MD290T355G	355	MDBU-200-B	3	23000 W 3.8 $\Omega$	3	Input voltage $\leq$ 440 VAC	2.5 $\times$ 3
	355	MDBU-200-C	3	23000 W 4.9 $\Omega$	3	Input voltage > 440 VAC	3.0 $\times$ 3
MD290T400P	400	MDBU-200-B	3	26000 W 3.4 $\Omega$	3	Input voltage $\leq$ 440 VAC	2.5 $\times$ 3
	400	MDBU-200-C	3	26000 W 4.3 $\Omega$	3	Input voltage > 440 VAC	3.0 $\times$ 3
MD290T400G	400	MDBU-200-B	3	26000 W 3.4 $\Omega$	3	Input voltage $\leq$ 440 VAC	2.5 $\times$ 3
	400	MDBU-200-C	3	26000 W 4.3 $\Omega$	3	Input voltage > 440 VAC	3.0 $\times$ 3
MD290T450P	450	MDBU-200-B	3	29000 W 3.0 $\Omega$	3	Input voltage $\leq$ 440 VAC	2.5 $\times$ 3
	450	MDBU-200-C	3	29000 W 3.9 $\Omega$	3	Input voltage > 440 VAC	3.0 $\times$ 3
MD290T450G	450	MDBU-200-B	3	29000 W 3.0 $\Omega$	3	Input voltage $\leq$ 440 VAC	2.5 $\times$ 3
	450	MDBU-200-C	3	29000 W 3.9 $\Omega$	3	Input voltage > 440 VAC	3.0 $\times$ 3
MD290T500P	500	MDBU-200-B	3	29000 W 3.0 $\Omega$	3	Input voltage $\leq$ 440 VAC	2.5 $\times$ 3
	500	MDBU-200-C	3	29000 W 3.9 $\Omega$	3	Input voltage > 440 VAC	3.0 $\times$ 3

Table 2-11 Braking component selection (three phase 200–240 V)

AC Drive Model	Applicable Motor (kW)	Braking Unit		125% Braking Torque (10% ED, Max. 10s)		Remarks	Minimum Braking Resistance (Ω)
		Model	QTY	Recommended Braking Resistor	QTY		
MD290-2T0.4G/0.7PB	0.75	Built-in		220 W 500 Ω	1	AC drive models ending with letter "B"	96
MD290-2T0.7G/1.1PB	1.1			440 W 260 Ω	1		96
MD290-2T1.1G/1.5PB	1.5			600 W 190 Ω	1		64
MD290-2T1.5G/2.2PB	2.2			740 W 150 Ω	1		64
MD290-2T2.2G/3.7PB	3.7			1100 W 100 Ω	1		32
MD290-2T3.7G/5.5PB	5.5			1500 W 75 Ω	1		32
MD290-2T5.5G/7.5PB	7.5			3000 W 38 Ω	1		20
MD290-2T7.5G/11PB	11			4000 W 32 Ω	1		20
MD290-2T11G/15P(B)	15	Built-in		4500 W 27 Ω	1	AC drive models ending with letter "B"	24
MD290-2T15G/18.5P(B)	18.5			6000 W 20 Ω	1		19.2
MD290-2T18.5G/22P(B)	22			7000 W 16 Ω	1		14.8
MD290-2T22G/30P(B)	30			9000 W 13 Ω	1		12.8
MD290-2T30G/37P(B)	37			11000 W 10.5 Ω	1		9.6
MD290-2T37G/45P(B)	45			15000 W 7.7 Ω	1		6.8
MD290-2T45G/55P	55			MDBUN-60-T	2		9000 W 10.0 Ω
	55	MDBUN-60-5T	2	9000 W 12.8 Ω	2	Input voltage > 440 VAC	10.5×2
MD290-2T55G/75P	75	MDBUN-60-T	2	11000 W 9.4 Ω	2	Input voltage ≤ 440 VAC	9.3×2
	75	MDBUN-60-5T	2	11000 W 10.5 Ω	2	Input voltage > 440 VAC	10.5×2



- ◆ The minimum braking resistance in the preceding table supports the operating condition with ED of 10% and the longest time for single braking of 10s.
- ◆ The default initial braking voltage for built-in braking units is 760 V. The default initial braking voltage is 670 V for external braking units MDBUN-60-T, MDBUN-90-T, and MDBU-200-B when the input voltage is lower than or equal to 440 VAC. The default initial braking voltage is 760 V for external braking units MDBUN-60-5T, MDBUN-90-5T, and MDBU-200-C when the input voltage is above 440 VAC. The resistance of the braking resistor can be adjusted with the initial braking voltage.
- ◆ The preceding table is for reference only. You can select the resistance and power of the braking resistor as required (the resistance cannot be lower than the reference value while the power may be higher than the reference value). Selection of the braking resistor model is determined by the generation power of motors and is also related to the system inertia, deceleration time and potential energy load. For systems with high inertia, and/or short deceleration time, and/or frequent braking, select a braking resistor with higher power and lower resistance.

## 2.7 External Operating Panels

### 1) External LED operating panel MD32NKE1

MD32NKE1 is an external operating panel applicable to the AC drive. It adopts the LED display and has the same operation mode as the operating panel on the AC drive. For details, see "[4 Panel Operations](#)". It is optional and easy for commissioning.




Figure 2-2 Mounting dimensions of MD32NKE1 (unit: mm)

### 2) External LCD operating panel MDKE9

MDKE9 is an optional external LCD operating panel. It supports copy, download, and modification of all parameters and is easy to use in both Chinese and English. The following figure shows its appearance and keys. (For details, see 19010321 MD290 Series AC Drive Advanced User Guide.)




Figure 2-3 Appearance of the MDKE9 external operating panel




Figure 2-4 Mounting dimensions of the MDKE9 external operating panel (unit: mm)

3) MDKE9 mounting base

Before installing the MDKE9 operating panel on the cabinet door, install the CP600-BASE1 (optional) base first. The mounting dimensions are shown below.




Figure 2-5 Sheet metal slot dimensions (unit: mm)




Figure 2-6 Mounting base dimension limits (unit: mm)

## 3 Installation and Wiring

### 3.1 Installation

#### 3.1.1 Installation Environment

- 1) Ambient temperature: The AC drive's service life is greatly influenced by the ambient temperature. Do not run the AC drive under a temperature exceeding the allowed temperature range (-10°C to +50°C).
- 2) Install the AC drive on a flame-retardant surface, and ensure that sufficient space is left around the enclosure to allow for efficient heat dissipation. The AC drive generates significant heat during working. Use screws to install the AC drive on the mounting bracket vertically.
- 3) Install the AC drive without strong vibration. Ensure that the mounting location is not affected by levels of vibration that exceeds 1 G. Keep the AC drive away from punch machines.
- 4) Ensure that the mounting location is away from direct sunlight, dampness, or water drops.
- 5) Ensure that the mounting location is protected against corrosive, combustible or explosive gases and vapors.
- 6) Ensure that the mounting location is free from oil and dust.




Figure 3-1 Installation environment requirements

- 7) The AC drive must be installed in a fireproof cabinet with doors that provide effective electrical and mechanical protection. The installation must conform to local and regional laws and regulations, and to relevant IEC requirements.

### 3.1.2 Backplate Mounting and Through-Hole Mounting

#### 1) Backplate mounting




Figure 3-2 Backplate mounting of MD290T0.4G/0.7PB to MD290T37G/45P(B) and MD290-2T0.4G/0.7PB to MD290-2T18.5G/22P(B)




Figure 3-3 Backplate mounting of MD290T45G/55P(B) to MD290T160G/200P and MD290-2T22G/30P(B) to MD290-2T55G/75P



**NOTE**

- ◆ In this mode, mount the AC drive using all mounting holes; otherwise, the AC drive may fall off or be damaged due to the unbalanced effect on the fixed part during long-time running.

2) Through-hole mounting




Figure 3-4 Through-hole mounting of MD290T0.4G/0.7PB to MD290T37G/45P(B) and MD290-2T0.4G/0.7PB to MD290-2T18.5G /22P(B)




Figure 3-5 Through-hole mounting of MD290T45G/55P(B) to MD290T160G/200P and MD290-2T22G/30P(B) to MD290-2T55G/75P

3) Through-hole mounting brackets

Table 3-1 Through-hole mounting bracket models (three phase 380–480 V)

Through-hole Mounting Bracket Model	AC Drive Model	Through-hole Mounting Bracket Model	AC Drive Model
MD500-AZJ-A1T1	MD290T0.4G/0.7PB	MD500-AZJ-A1T5	MD290T18.5G/22P(B) (-T)
	MD290T0.7G/1.1PB		MD290T22G/30P(B)(-T)
	MD290T1.1G/1.5PB	MD500-AZJ-A1T6	MD290T30G/37P(B)
	MD290T1.5G/2.2PB		MD290T37G/45P(B)
	MD290T2.2G/3.0PB	MD500-AZJ-A1T7	MD290T45G/55P(B)
	MD290T3.0G/3.7PB		MD290T55G/75P(B)
MD500-AZJ-A1T2	MD290T3.7G/5.5PB	MD500-AZJ-A1T8	MD290T75G/90P(B)
	MD290T5.5G/7.5PB		MD290T90G/110P
MD500-AZJ-A1T3	MD290T7.5G/11PB	MD500-AZJ-A1T9	MD290T110G/132P
	MD290T11G/15PB		MD290T132G/160P
MD500-AZJ-A1T4	MD290T15G/18.5PB		MD290T160G/200P

Table 3-2 Through-hole mounting bracket models (three phase 200–240 V)

Through-hole Mounting Bracket Model	AC Drive Model	Through-hole Mounting Bracket Model	AC Drive Model
MD500-AZJ-A1T1	MD290-2T0.4G/0.7PB	MD500-AZJ-A1T6	MD290-2T15G/18.5P(B)
	MD290-2T0.7G/1.1PB		MD290-2T18.5G/22P(B)
	MD290-2T1.1G/1.5PB	MD500-AZJ-A1T7	MD290-2T22G/30P(B)
	MD290-2T1.5G/2.2PB		MD290-2T30G/37P(B)
MD500-AZJ-A1T2	MD290-2T2.2G/3.7PB	MD500-AZJ-A1T8	MD290-2T37G/45P(B)
	MD290-2T3.7G/5.5PB		MD290-2T45G/55P
MD500-AZJ-A1T3	MD290-2T5.5G/7.5PB		MD290-2T55G/75P
MD500-AZJ-A1T4	MD290-2T7.5G/11PB		
MD500-AZJ-A1T5	MD290-2T11G/15P(B)	-	-

**3.1.3 Mounting in the Cabinet**

Only one AC drive of models MD290T200G(-L) to MD290T450G(-L) and MD290T220P(-L) to MD290T500P(-L) can be mounted in a cabinet and ventilation space must be considered. Follow the following guidance for specific model and application scenarios.

■ Direct discharging cabinet (without fans on the top)




Figure 3-6 Direct discharging cabinet

Table 3-3 Specification of the direct discharging cabinet

AC Drive Model		Quantity of Fans	Total Air Volume (CFM)	Effective Area of Cabinet Top Air Inlet (mm <sup>2</sup> )	Effective Area of Cabinet Top Air Outlet (mm <sup>2</sup> )
MD290T132G/160P		2	541	31809	50894
MD290T160G/200P		2	620	31809	50894
MD290T200G(-L)	MD290T220P(-L)	2	586	31809	50894
MD290T250P(-L)					
MD290T220G(-L)	MD290T280P(-L)	2	722	31809	50894
MD290T250G(-L)	MD290T315P(-L)	3	789	47713	76341
MD290T280G(-L)	MD290T355P(-L)	3	882	47713	76341
MD290T315G(-L)	MD290T400P(-L)	3	644	47713	76341
MD290T355G(-L)	MD290T450P(-L)	3	796	47713	76341
MD290T400G(-L)	MD290T500P(-L)	3	796	47713	76341
MD290T450G(-L)		3	796	47713	76341

Note:

- ◆ CFM = 0.0283 m<sup>3</sup>/min
- ◆ "Effective Area" indicates the through-hole area.

■ Cabinet with fans on the top




Figure 3-7 Cabinet with fans on the top

Table 3-4 Specification of the cabinet with fans on the top

AC Drive Model		Quantity of Fans	Total Air Volume (CFM)	Effective Area of Cabinet Top Air Inlet (mm <sup>2</sup> )	Max. Air Volume Required by the Top Fan (CFM)	Effective Area of Cabinet Top Air Outlet (mm <sup>2</sup> )
MD290T132G/160P		2	541	31809	649	S = 0.942x N x (Dout2 - DHUB2)
MD290T160G/200P		2	620	31809	744	
MD290T200G(-L)	MD290T220P(-L)	2	586	31809	703	In the preceding formula, N indicates the number of top fans, Dout indicates the diameter of the top fan, and DHUB indicates the diameter of the top fan center HUB.
MD290T250P(-L)						
MD290T220G(-L)	MD290T280P(-L)	2	722	31809	866	
MD290T250G(-L)	MD290T315P(-L)	3	789	47713	947	
MD290T280G(-L)	MD290T355P(-L)	3	882	47713	1058	
MD290T315G(-L)	MD290T400P(-L)	3	644	47713	773	
MD290T355G(-L)	MD290T450P(-L)	3	796	47713	955	
MD290T400G(-L)	MD290T500P(-L)	3	796	47713	955	
MD290T450G(-L)		3	796	47713	955	

Note:

◆ CFM = 0.0283 m<sup>3</sup>/min

◆ "Effective Area" indicates the through-hole area.

## 3.2 Wiring

### 3.2.1 Standard Wiring Diagram

As shown in the following figure, the wiring part marked by the double-headed arrow differs between three-phase 380 to 480 V 0.4G/0.7PB to 75G/90P(B) models and 90G/100P to 450G/500P models, and between three-phase 200 to 240 V 0.4G/0.7PB to 37G/45P(B) models and 45G/55P and above models.




Figure 3-8 Typical wiring

### 3.2.2 Main Circuit Terminals




Figure 3-9 Terminal arrangement in MD290T0.4G/0.7PB to MD290T15G/18.5PB and MD290-2T0.4G/0.7PB to MD290-2T7.5G/11PB




Figure 3-10 Terminal arrangement in MD290T18.5G/22P(B) to MD290T160G/200P and MD290-2T11G/15P(B) to MD290-2T55G/75P




Figure 3-11 Terminal arrangement in MD290T200G to MD290T450G and MD290T220P to MD290T500P

Table 3-5 Description of main circuit terminals

Terminal	Name	Description
R, S, T	Three-phase power supply input terminals	Connected to AC input three-phase power supply.
(+), (-)	DC bus positive and negative terminals	Common DC bus input, connected to the external braking unit for AC drives of 90 kW and above
(+), BR	Braking resistor connection terminals	Connected to the external braking resistor for AC drives of 75 kW and below
U, V, W	AC drive output terminals	Connected to a three-phase motor
	Ground (PE) terminal	Grounding connection

### 3.2.3 Control Circuit Terminals




Figure 3-12 Control circuit terminal arrangement

Table 3-6 Description of control circuit terminals

Type	Terminal Mark	Terminal Name	Description
Power supply	+10 V-GND	+10 V power supply	Provides +10 V power supply to an external unit. Its maximum output current is 10 mA. Generally used to supply an external potentiometer of 1 to 5 k $\Omega$
	+24V-COM	+24 V power supply	Provides +24 V power supply to an external unit. Generally used for power supply for DI/DO terminals and external sensors. Maximum output current: 200 mA <sup>[1]</sup>
	OP	Input terminal for external power supply	Connected to +24 V by default. When DI1 to DI5 need to be driven by external signals, OP must be disconnected from + 24 V and connected to an external power supply.
Analog input	AI1-GND	Analog input 1	Voltage range of inputs: 0 to 10 VDC Input impedance: 22 k $\Omega$
	AI2-GND	Analog input 2	Either a voltage or current input, determined by jumper J9 Input voltage range: 0 to 10 VDC Input current range: 0 to 20 mA Input impedance: 22 k $\Omega$ (voltage input), 500 $\Omega$ or 250 $\Omega$ (current input) decided by J10 <sup>[2]</sup>
Digital input	DI1- OP	Digital input 1	Optically-coupled isolation compatible with dual-polarity inputs Input impedance: 1.39 k $\Omega$ Voltage range for inputs: 9 to 30 V
	DI2- OP	Digital input 2	
	DI3- OP	Digital input 3	
	DI4- OP	Digital input 4	
	DI5- OP	High-speed pulse input	In addition to having the same features as DI1 to DI4, DI5 can also be used for high-speed pulse inputs. Maximum input frequency: 100 kHz Input impedance: 1.03 k $\Omega$
Analog output	AO1-GND	Analog output 1	Either a voltage or current output, determined by jumper J7. Output voltage range: 0 to 10 V Output current range: 0 to 20 mA

Type	Terminal Mark	Terminal Name	Description
Digital output	DO1-CME	Digital output 1	Optically-coupled isolation, dual-polarity open-collector output Output voltage range: 0 to 24 V Output current range: 0 to 50 mA Note that CME and COM are internally insulated, but are shorted externally by a jumper. In this case, DO1 is driven by +24 V by default. Remove the jumper link if you need to apply external power to DO1.
	FM-COM	High-speed pulse output	Controlled by F5-00 (FM terminal output selection). Maximum output frequency: 100 kHz When used as an open-collector output, the specification is the same as for DO1.
Relay output	T/A-T/B	Normally-closed (NC) terminal	Contact driving capacity: 250 VAC, 3 A, Cos $\Phi$ = 0.4 30 VDC, 1 A
	T/A-T/C	Normally-open (NO) terminal	
Auxiliary interfaces	J13	Extension card interface	Interface for the 28-core terminal and optional cards (I/O extension card, PLC card, and various bus cards)
	J11	External operating panel interface	Connected to an external operating panel.
Jumper <sup>[3]</sup>	J7	AO1 output selection	Either a voltage or a current output. Voltage output by default
	J9	AI2 input selection	Either a voltage or a current input. Voltage input by default
	J10	AI2 input impedance selection	Either 500 $\Omega$ or 250 $\Omega$ input. 500 $\Omega$ input by default

- [1] When the ambient environment is above 23°C, the output current must be de-rated for 1.8 mA per 1°C rise. The maximum output current is 170 mA at 40°C. When OP is shorted to 24 V, the current of the DI must also be considered.
- [2] Select 500  $\Omega$  or 250  $\Omega$  input impedance according to the with-load capacity of signal source. For example, if 500  $\Omega$  is selected, the maximum output voltage of signal source cannot be lower than 10 V so that AI2 can measure 20 mA current.
- [3] For positions of jumpers J7, J9 and J10, see Figure 3-12.

Power grid system requirements:

- ◆ The AC drive is applicable to power grid systems with neutral points grounded. If the AC drive is used in an IT power system (where the neutral point is not grounded), screws 1 and 2 shown in the following figure must be screwed out to remove the jumpers of the voltage-dependent resistor (VDR) and EMC. Failure to comply may result in personal injury or damage to the AC drive.
- ◆ If a leakage circuit breaker is configured and the leakage protector is tripped during startup, you can remove the EMC jumper (screw 2 shown in the following figure).




Figure 3-13 VDR and EMC jumpers

## 4 Panel Operations

### 4.1 Introduction

The LED operating panel allows you to set and modify parameters, monitor system status, and start or stop the AC drive. For details, see 19010321 MD290 Series AC Drive Advanced User Guide. An external LED (MD32NKE1) or LCD (MDKE9) operating panel is also available as an option. For details, see ["2.7 External Operating Panels"](#).




Figure 4-1 Details of the operating panel

### 4.2 Keys on the Operating Panel

Table 4-1 Function of keys on the operating panel

Key	Name	Function
	Programming	Enter Level I menu, and exit all other levels without saving.
	Enter	Enter each level of menu interface and confirm parameter change.
	Increment	Increase the displayed value when editing a parameter value.
	Decrement	Decrease the displayed value when editing a parameter value.
	Shift	Select the displayed parameter in the STOP or RUNNING status. Select the digit to be modified when modifying a parameter value.
	RUN	Start the AC drive when using the operating panel control mode.

Key	Name	Function
	Stop/Reset	Stop the AC drive when the AC drive is in the RUNNING status. Perform a reset operation when the AC drive is in the FAULT status.
	Multifunction	Perform a function switchover as defined by the setting of F7-01 (MF.K key function selection).
	Menu mode selection	Switch over between menu modes as defined by the setting of FP-03 (Selection of individualized parameter display).

### 4.3 Indicators on the Operating Panel

indicates that the light turns on, indicates that the light turns off, and indicates that the light flashes.

Table 4-2 Indicators on the operating panel

State	Indication
RUN Running status indicators	RUN OFF indicates the STOP status.
	RUN ON indicates the RUNNING status.
LOCAL/REMOT Running command indicators	LOCAL/ REMOT OFF indicates under operating panel control.
	LOCAL/ REMOT ON indicates under terminal control.
	LOCAL/ REMOT FLASHING indicates under serial communication control.
FWD/REV Forward and reverse rotation indicators	FWD/REV OFF indicates forward motor rotation.
	FWD/REV ON indicates reverse motor rotation.
TUNE/TC Auto-tuning, torque control and fault indicators	TUNE/ TC OFF indicates that the AC drive is normal.
	TUNE/ TC ON indicates the torque control mode.
	TUNE/ TC FLASHING SLOWLY (once a second) indicates auto-tuning status.
	TUNE/ TC FLASHING QUICKLY (four times a second) indicates a fault condition.
Hz — RPM —  A — % —  V	Hz for frequency
Hz — RPM —  A — % —  V	A for current
Hz — RPM —  A — % —  V	V for voltage
Hz — RPM —  A — % —  V	RPM for motor speed
Hz — RPM —  A — % —  V	Percentage

## 5 Basic Operations and Trial Run

### 5.1 Quick Commissioning




Figure 5-1 Quick commissioning

### 5.2 Precautions Before Power-on

Be sure to check the following items before powering on the AC drive.

Item	Description
Voltage	The voltage is AC 380 to 480 V and 50/60 Hz.
	The input terminals R, S, and T are correctly connected.
	The AC drive is connected to the motor properly.
Connection of AC drive output terminals and motor terminals	The AC drive output terminals U, V, and W are firmly connected to the motor terminals.
Connection of terminals in the control circuit	Terminals of the control circuit are firmly connected to other control devices.
Status of control terminals	All terminals of the control circuit are OFF (the AC drive is not running).
Load	The motor is idle and not connected to the mechanical system.

### 5.3 Status Display After Power-on

The following table lists the display on the operating panel after the AC drive is powered on.

State	Display	Description
Normal	<b>5000</b>	The default value 50.00 Hz is displayed.
Fault	<b>Err02</b>	The AC drive stops and displays an error code.

### 5.4 Parameter Initialization

You can restore the AC drive to factory parameters. After initialization, FP-01 is automatically reset to 0.

FP-01	Parameter initialization	Default	0
	Setting Range	0	No operation
1		Restore factory parameters except motor parameters	
2		Clear records	
4		Back up current user parameters	
501		Restore user backup parameters	

1: Restore factory parameters except motor parameters

When FP-01 is set to 1, most of the parameters are restored to the factory default settings. However, motor parameters, F0-22 (Frequency reference resolution), error records, F7-09 (Accumulative running time), F7-13 (Accumulative power-on time), F7-14 (Accumulative power consumption), and F7-07 (Heatsink temperature of AC drive) cannot be restored.

2: Clear records

Error records, F7-09 (Accumulative running time), F7-13 (Accumulative power-on time), and F7-14 (Accumulative power consumption) are cleared.

4: Back up current user parameters

Parameters set by the current user are backed up. Values of all the current parameters are backed up for restoration after an error caused by parameter adjustment occurs.

501: Restore user backup parameters

Restore parameters backed up by setting FP-01 to 4.

## 5.5 Motor Control Modes

Parameter	Description	Scenario
F0-01: Motor control mode	F0-01 = 2: V/F control (open-loop speed control)	It is applicable to scenarios having no high requirement on load (fans and pumps) or using one AC drive to drive multiple motors.

## 5.6 Auto-tuning

You can obtain parameters of a controlled motor through motor auto-tuning. Motor auto-tuning methods include dynamic auto-tuning, static auto-tuning 1, and static auto-tuning 2. You can enter the motor parameters manually.

Auto-tuning Method	Application	Result
Dynamic no-load auto-tuning F1-37 = 2	Applied to applications where motors can be disconnected from the load.	Best
Dynamic auto-tuning with load F1-37 = 2	Applied to applications where motors cannot be disconnected from the load. The load friction force is small and the motor is appropriately idle when running at a constant speed. The effect is better with a smaller friction force.	Better
Static auto-tuning 1 F1-37 = 1	Applied to applications where motors cannot be disconnected from the load and dynamic auto-tuning is not allowed.	Good
Static auto-tuning 2 F1-37 = 3	Applied to applications where motors cannot be disconnected from the load and dynamic auto-tuning is not allowed. This mode is recommended for static auto-tuning. It lengthens the auto-tuning time compared to static auto-tuning 1.	Better
Manual parameter input	Applied to applications where motors cannot be disconnected from the load. Copy parameters of motors of the same model which have been auto-tuned to F1-00 (Motor type selection) to F1-10 (No-load current).	Better

Auto-tuning methods are described below.

Motor 1 is used to describe motor auto-tuning methods. If you need to perform auto-tuning on motor 2, set F0-24 (Motor parameter group selection) to 1 (Motor parameter group 2).

Step 1: If the motor can be disconnected from the load, cut off the power, and disconnect the motor from the load to have the motor run without load.

Step 2: Power on the AC drive. Set F0-02 (Running command selection) to 0 (Operating panel) to select the operating panel as the running command.

Step 3: Input motor nameplate parameters (F1-00 to F1-05) correctly. Set the following parameters according to the motor:

Motor	Parameter
Motor 1	F1-00: Motor type selection F1-01: Rated motor power F1-02: Rated motor voltage F1-03: Rated motor current F1-04: Rated motor frequency F1-05: Rated motor speed
Motor 2	A2-00 (Motor type selection) to A2-05 (Rated motor speed) have the same definition.

Step 4: For an asynchronous motor, set F1-37 (Auto-tuning selection) (A2-37 in case of Motor 2) to 2 (Asynchronous motor dynamic auto-tuning) and press "ENTER". "TUNE" is displayed, as shown in the following figure:



Press "RUN" on the operating panel. The AC drive drives the motor to accelerate/ decelerate and run in forward/reverse direction. The RUN indicator becomes ON and auto-tuning lasts for about 2 minutes. After the preceding display disappears and the operating panel returns to normal parameter display state, auto-tuning is complete.

After auto-tuning, the following motor parameters are calculated:

Motor	Parameter
Motor 1	F1-06: Stator resistance F1-07: Rotor resistance F1-08: Leakage inductive reactance F1-09: Mutual inductive reactance F1-10: No-load current
Motor 2	A2-06 to A2-10 have the same definition.

If the motor cannot be disconnected from the load, set F1-37 (A2-37 in case of Motor 2) to 3 (Asynchronous motor complete static auto-tuning) and press "RUN" on the operating panel. Auto-tuning starts.

## 6 Troubleshooting

### 6.1 Fault Codes and Solutions

Troubleshoot the faults occurred during operating the AC drive as follows.

Fault Code	Fault Name	Possible Cause	Solution
<b>Err02</b>	Overcurrent during acceleration	A grounding fault or short circuit exists in the output circuit.	Check whether short-circuit occurs on the motor or contactor.
		The acceleration time is too short.	Increase the acceleration time.
		The overcurrent stall prevention parameters are set improperly.	Ensure that current limit is enabled (F3-19 = 1). The setting of F3-18 (Current limit level) is too high. Adjust it between 120% and 150%. The setting of F3-20 (Current limit gain) is too low. Adjust it between 20 and 40.
		Customized torque boost or V/F curve is not appropriate.	Adjust the customized torque boost or V/F curve.
		The motor is started while spinning.	Enable the flying start function or start the motor after it stops spinning.
		The AC drive suffers external interference.	View historical fault records. If the current value is far from the overcurrent level, find the interference source. If an external interference does not exist, the driver board or Hall element may be faulty.

Fault Code	Fault Name	Possible Cause	Solution
<b>Err03</b>	Overcurrent during deceleration	A grounding fault or short circuit exists in the output circuit.	Check whether short-circuit or open-circuit occurs on the motor.
		The deceleration time is too short.	Increase the deceleration time.
		The overcurrent stall prevention parameters are set improperly.	Ensure that current limit is enabled (F3-19 = 1). The setting of F3-18 (Current limit level) is too high. Adjust it between 120% and 150%. The setting of F3-20 (Current limit gain) is too low. Adjust it between 20 and 40.
		The braking unit and braking resistor are not installed.	Install the braking unit and braking resistor.
		The AC drive suffers external interference.	View historical fault records. If the current value is far from the overcurrent level, find the interference source. If an external interference does not exist, the driver board or Hall element may be faulty.
<b>Err04</b>	Overcurrent at constant speed	A grounding fault or short circuit exists in the output circuit.	Check whether short-circuit or open-circuit occurs on the motor.
		The overcurrent stall prevention parameters are set improperly.	Ensure that current limit is enabled (F3-19 = 1). The setting of F3-18 (Current limit level) is too high. Adjust it between 120% and 150%. The setting of F3-20 (Current limit gain) is too low. Adjust it between 20 and 40.
		The AC drive power class is low.	If the output current exceeds the rated motor current or rated output current of the AC drive during stable running, use an AC drive of higher power class.
		The AC drive suffers external interference.	View historical fault records. If the current value is far from the overcurrent level, find the interference source. If an external interference does not exist, the driver board or Hall element may be faulty.

Fault Code	Fault Name	Possible Cause	Solution
<b>Err05</b>	Overvoltage during acceleration	The input voltage is too high.	Adjust the input voltage to the normal range.
		An external force drives the motor during acceleration.	Cancel the external force or install a braking resistor.
		The overvoltage stall prevention parameters are set improperly.	Ensure that the voltage limit function is enabled (F3-23 = 1). The setting of F3-22 (Voltage limit) is too high. Adjust it between 700 V and 770 V. The setting of F3-24 (Frequency gain for voltage limit) is too low. Adjust it between 30 and 50.
		The braking unit and braking resistor are not installed.	Install the braking unit and braking resistor.
		The acceleration time is too short.	Increase the acceleration time.
<b>Err06</b>	Overvoltage during deceleration	The overvoltage stall prevention parameters are set improperly.	Ensure that the voltage limit function is enabled (F3-23 = 1). The setting of F3-22 (Voltage limit) is too high. Adjust it between 700 V and 770 V. The setting of F3-24 (Frequency gain for voltage limit) is too low. Adjust it between 30 and 50.
		An external force drives the motor during deceleration.	Cancel the external force or install a braking resistor.
		The deceleration time is too short.	Increase the deceleration time.
		The braking unit and braking resistor are not installed.	Install the braking unit and braking resistor.
<b>Err07</b>	Overvoltage at constant speed	The overvoltage stall prevention parameters are set improperly.	Ensure that the voltage limit function is enabled (F3-23 = 1). The setting of F3-22 (Voltage limit) is too high. Adjust it between 700 V and 770 V. The setting of F3-24 (Frequency gain for voltage limit) is too low. Adjust it between 30 and 50. The setting of F3-26 (Frequency rise threshold during voltage limit) is too low. Adjust it between 5 Hz and 20 Hz.
		An external force drives the motor during acceleration.	Cancel the external force or install a braking resistor.

Fault Code	Fault Name	Possible Cause	Solution
<b>Err08</b>	Control power fault	The input voltage exceeds the setting range.	Adjust the input voltage within the setting range.
<b>Err09</b>	Undervoltage	An instantaneous power failure occurs.	Enable the power dip ride through function (F9-59 $\neq$ 0).
		The AC drive's input voltage is not within the permissible range.	Adjust the voltage to the normal range.
		The bus voltage is abnormal.	Contact the agent or Inovance.
		The rectifier bridge, pre-charge resistor, driver board, or control board is abnormal.	Contact the agent or Inovance.
<b>Err10</b>	AC drive overload	The load is too heavy or locked-rotor occurs on the motor.	Reduce the load or check motor and mechanical conditions.
		The AC drive power class is low.	Replace an AC drive of higher power class.
<b>Err11</b>	Motor overload	F9-01 (Motor overload protection gain) is set improperly.	Set F9-01 (Motor overload protection gain) correctly.
		The load is too heavy or locked-rotor occurs on the motor.	Reduce the load or check motor and mechanical conditions.
<b>Err12</b>	Input phase loss	Input phase loss occurs.	Eliminate faults in external circuits.
		The driver board, lightning protection board, main control board, or rectifier bridge is abnormal.	Contact the agent or Inovance.
<b>Err13</b>	Output phase loss	The motor is faulty.	Check and ensure that the motor is free of open circuit.
		The cable connecting the AC drive and the motor is abnormal.	Eliminate external faults.
		The AC drive's three-phase outputs are unbalanced when the motor is running.	Check whether the motor three-phase winding is normal.
		The driver board or the IGBT is abnormal.	Contact the agent or Inovance.

Fault Code	Fault Name	Possible Cause	Solution
<b>Err14</b>	IGBT overheat	The ambient temperature is too high.	Lower the ambient temperature.
		The ventilation is clogged.	Clean the ventilation.
		The fan is damaged.	Replace the cooling fan.
		The thermistor of IGBT is damaged.	Replace the thermistor.
		The IGBT is damaged.	Replace the IGBT.
<b>Err15</b>	External fault	An external fault signal is input using the DI.	Eliminate external faults, and confirm that the mechanical condition allows restart (F8-18) and reset the operation.
		An external fault signal is input using virtual I/O.	Confirm that the virtual I/O parameters in group A1 are set correctly and reset the operation.
<b>Err16</b>	Communication fault	The host controller is in abnormal state.	Check the cable of the host controller.
		The communication cable is abnormal.	Check the communication cables.
		The serial port communication protocol (F0-28) of the extension communication card is set improperly.	Set F0-28 (Serial port communication protocol) for the extension communication card correctly.
		Communication parameters in group Fd are set improperly.	Set communication parameters in group Fd properly.
		If the fault still exists after all the preceding checkings are done, restore the default settings.	
<b>Err17</b>	Contactor fault	The driver board and power supply are abnormal.	Replace the driver board or power supply board.
		The contactor is abnormal.	Replace the contactor.
		The lightning protection board is abnormal.	Replace the lightning protection board.
<b>Err18</b>	Current detection fault	The Hall element is abnormal.	Replace the Hall element.
		The driver board is abnormal.	Replace the driver board.

Fault Code	Fault Name	Possible Cause	Solution
<b>Err19</b>	Motor auto-tuning fault	Motor parameters are not set according to the nameplate.	Set motor parameters correctly according to the nameplate.
		Motor auto-tuning times out.	Check whether the AC drive and motor are connected correctly.
<b>Err21</b>	EEPROM read-write fault	The EEPROM chip is damaged.	Replace the main control board.
<b>Err23</b>	Short circuit to ground	The motor is short-circuited to the ground.	Replace the cable or motor.
<b>Err26</b>	Accumulative running time reached	The accumulative running time reached the set value.	Clear the record by parameter initialization.
<b>Err27</b>	User-defined fault 1	The signal of user-defined fault 1 is input through the multi-functional terminal DI.	Perform the reset operation.
		The signal of user-defined fault 1 is input through the virtual I/O.	Perform the reset operation.
<b>Err28</b>	User-defined fault 2	The signal of user-defined fault 2 is input through the multi-functional terminal DI.	Perform the reset operation.
		The signal of user-defined fault 2 is input through the virtual I/O.	Perform the reset operation.
<b>Err29</b>	Accumulative power-on time reached	The accumulative power-on time reached the set value.	Clear the record by parameter initialization.
<b>Err30</b>	Load loss	The operation current of the AC drive is lower than F9-64 (Load loss detection level) and F9-65 (Load loss detection level).	Check whether the load is disconnected or ensure that F9-64 (Load loss detection level) and F9-65 (Load loss detection time) are set based on the actual conditions.
<b>Err31</b>	PID Feedback loss during running	PID feedback is smaller than FA-26 (Detection level of PID feedback loss).	Check the PID feedback signal or set FA-26 (Detection level of PID feedback loss) correctly.
<b>Err40</b>	Pulse-by-pulse current limit fault	The load is too heavy or locked-rotor occurs on the motor.	Reduce the load or check motor and mechanical conditions.
		The AC drive power class is low.	Replace an AC drive of higher power class.

Fault Code	Fault Name	Possible Cause	Solution
<b>Err41</b>	Motor switchover fault during running	Motor switchover is performed using a terminal during running of the AC drive.	Perform motor switchover after the AC drive stops.
<b>Err45</b>	Motor overheat	Cable connection of the temperature sensor becomes loose.	Check cable connection of the temperature sensor.
		The motor temperature is too high.	Increase the carrier frequency or take other measures to cool the motor.
<b>Err55</b>	Slave error in master-slave control	Check the slave.	Troubleshoot the problem according to the slave fault code.
<b>Err61</b>	Braking unit overload	The resistance of braking resistor is too low.	Use a braking resistor of higher resistance.
<b>Err62</b>	Short-circuit of braking circuit	The braking module is abnormal.	Contact the agent or Inovance.

## 6.2 Common Symptoms and Solutions

No.	Fault Symptom	Possible Cause	Solution
1	There is no display upon power-on.	There is no power supply to the AC drive or the power input to the AC drive is too low.	Check the power supply.
		The switching power supply on the driver board of the AC drive is faulty.	Check the bus voltage.
		Wires between the control board and driver board and between the control board and operating panel break.	Re-connect the 8-pin wire and 40-pin wire.
		The pre-charge resistor of the AC drive is damaged.	Contact the agent or Inovance.
		The control board or the operating panel is faulty.	
		The rectifier bridge is damaged.	

No.	Fault Symptom	Possible Cause	Solution
2	"HC" is displayed upon power-on.	Cable connection between the driver board and control board is in poor contact.	Re-connect the 8-pin wire and 28-pin wire.
		Related components on the control board are damaged.	Contact the agent or Inovance.
		The motor or motor cable is short-circuited to ground.	
		The Hall element is faulty.	
3	"Err23" is displayed upon power-on.	The motor or the motor cable is short-circuited to the ground.	Check the insulation status of the motor and the output cable with a megger.
		The AC drive is damaged.	Contact the agent or Inovance.
4	The AC drive display is normal at power-on, but after running the AC drive displays "HC" and stops immediately.	The cooling fan is damaged or does not rotate.	Replace the damaged fan.
		The cable of the external control terminal is short-circuited.	Eliminate the external short-circuit fault.
5	"Err14" (IGBT overheat) is detected frequently.	The setting of carrier frequency is too high.	Reduce F0-15 (Carrier frequency).
		The cooling fan is damaged, or the ventilation is clogged.	Replace the cooling fan and clean the ventilation.
		Components (thermal coupler or others) inside the AC drive are damaged.	Contact the agent or Inovance.
6	The motor does not rotate after the AC drive runs.	There is a motor or motor cable problem.	Check that cabling between the AC drive and the motor is normal.
		The motor parameters in group F1 are set improperly.	Restore the factory parameters and reset the following parameters properly: <ul style="list-style-type: none"> <li>◆ F0-01 (Motor 1 control mode) and F0-02 (Running command selection)</li> <li>◆ F3-01 (Torque boost) in V/F control under heavy-load start</li> </ul>
		Cable connection between the driver board and control board is in poor contact.	Re-connect wirings and ensure secure connection.
		The driver board is faulty.	Contact the agent or Inovance.

No.	Fault Symptom	Possible Cause	Solution
7	DI terminals are disabled.	The related parameters are set incorrectly.	Check and reset the parameters in group F4 again.
		The external signal is incorrect.	Re-connect the external signal cable.
		The jumper across OP and +24 V becomes loose.	Re-confirm the jumper bar across OP and +24 V.
		The control board is faulty.	Contact the agent or Inovance.
8	The AC drive detects overcurrent and overvoltage frequently.	The motor parameters in group F1 are set improperly.	Set the motor parameters in group F1 or perform motor auto-tuning again.
		The acceleration/ deceleration time is improper.	Set proper acceleration/ deceleration time.
		The load fluctuates.	Contact the agent or Inovance.
9	"Err17" is detected upon power-on or running.	The pre-charge contactor is not closed.	<ul style="list-style-type: none"> <li>◆ Check whether the contactor cable is loose.</li> <li>◆ Check whether the contactor is faulty.</li> <li>◆ Check whether 24 V power supply of the contactor is faulty.</li> <li>◆ Contact the agent or Inovance.</li> </ul>
10	The brake torque of the motor is insufficient when the motor is in the deceleration or decelerate to stop state.	The overvoltage stall protection takes effect.	If the braking resistor has been configured, set F3-23 (Voltage limit selection) to 0 (Disabled).

## 7 Maintenance

### 7.1 Routine Maintenance

Check the following items daily to ensure normal running and prevent damage to the AC drive. Copy this checklist and sign the "Checked" column after each inspection.

Inspection Item	Inspection Points	Solutions	Checked
Motor	Inspect whether the abnormal sounds and vibration occur on the motor.	<ul style="list-style-type: none"> <li>◆ Check whether the mechanical connection is normal.</li> <li>◆ Check whether output phase loss occurs on the motor.</li> <li>◆ Check whether retaining screws of the motor are tightened.</li> </ul>	
Fan	Inspect whether the cooling fan of the AC drive and motor work abnormally.	<ul style="list-style-type: none"> <li>◆ Check running of the cooling fan of the AC drive.</li> <li>◆ Check whether the cooling fan of the motor is normal.</li> <li>◆ Check whether the ventilation is clogged.</li> <li>◆ Check whether the ambient temperature is within the permissible range.</li> </ul>	
Installation environment	Inspect whether the cabinet and cable duct are abnormal.	<ul style="list-style-type: none"> <li>◆ Check input and output cables for damaged insulation.</li> <li>◆ Check for vibration of the hanging bracket.</li> <li>◆ Check whether ground bars and terminals become loose or get corroded.</li> </ul>	
Load	Inspect whether the running current of the AC drive exceeds the rated current of the AC drive and motor for a certain period.	<ul style="list-style-type: none"> <li>◆ Check whether motor parameters are set properly.</li> <li>◆ Check whether the motor is overloaded.</li> <li>◆ Check whether the mechanical vibration is severe (allowed range: &lt; 1 g).</li> </ul>	
Input voltage	Inspect whether the power voltage of the main and control circuits is within the allowed range.	<ul style="list-style-type: none"> <li>◆ Check that the input voltage is within the allowed range.</li> <li>◆ Check whether start of heavy load exists.</li> </ul>	

## 7.2 Periodic Inspection

Inspection Item	Inspection Point	Solution	Checked
General	Inspect for wastes, dirt, and dust on the surface of the AC drive.	<ul style="list-style-type: none"> <li>◆ Check whether the cabinet of the AC drive is powered off.</li> <li>◆ Use a vacuum cleaner to suck up wastes and dust to prevent direct touching.</li> <li>◆ Wipe stubborn stains with alcohol and wait until the alcohol evaporates.</li> </ul>	
Cables	<ul style="list-style-type: none"> <li>◆ Inspect power cables and connections for discoloration.</li> <li>◆ Inspect wiring insulation for aging or wear.</li> </ul>	<ul style="list-style-type: none"> <li>◆ Replace cracked cables.</li> <li>◆ Replace damaged terminals.</li> </ul>	
Peripheral devices such as relay and contactor	<ul style="list-style-type: none"> <li>◆ Check whether the contactor is loose or abnormal noise exists during operation.</li> <li>◆ Check whether short-circuit, water stain, expansion, or cracking occurs on peripheral devices.</li> </ul>	<ul style="list-style-type: none"> <li>◆ Replace abnormal peripheral devices.</li> </ul>	
Ventilation	<ul style="list-style-type: none"> <li>◆ Inspect whether the ventilation and heatsink are clogged.</li> <li>◆ Check whether the fan is damaged.</li> </ul>	<ul style="list-style-type: none"> <li>◆ Clean the ventilation.</li> <li>◆ Replace the fan.</li> </ul>	
Control circuit	<ul style="list-style-type: none"> <li>◆ Inspect for control components in poor contact.</li> <li>◆ Inspect for loose terminal screws.</li> <li>◆ Inspect for control cables with cracked insulation.</li> </ul>	<ul style="list-style-type: none"> <li>◆ Clear away foreign matters on the surface of control cables and terminals.</li> <li>◆ Replace damaged or corroded control cables.</li> </ul>	

## 7.3 Replacement of Wear Parts

### 7.3.1 Service Life of Wear Parts

The service life of fans and electrolytic DC bus capacitors is related to the operating environment and maintenance status. The general service life is listed as follows.





Wear Part	Service Life <sup>[1]</sup>
Fan	≥ 5 years
Electrolytic capacitor	≥ 5 years

[1] You can determine when to replace these parts according to the actual operating time.

- Ambient temperature: 40°C
- Load rate: 80%
- Operating rate: 24 hours per day


### 7.3.2 Replacing Cooling Fans

- 1) Possible damage causes: bearing worn and blade aging
- 2) Replacement determination criteria: whether there is crack on the blade; whether there is abnormal vibration noise upon startup; whether the blade runs abnormally
- 3) Replacement notes:
  - To remove the cooling fan, decompress the fan cover hook and pull the cover out.
  - After replacing the fan, check that the air flow direction is upright.

Removing the Fan [MD290T45G/55P(B) to MD290T160G/200P, MD290-2T22G/30P(B) to MD290-2T55G/75P]		
<p>① Disconnect the fan power cable connector from the AC drive. (Top view)</p> 	<p>② Remove the four screws from the fan cover using a screwdriver.</p> 	<p>③ Remove the fan and fan cover from the AC drive.</p> 
Installing the Fan [MD290T45G/55P(B) to MD290T160G/200P, MD290-2T22G /30P(B) to MD290-2T55G /75P]		
<p>① Install the fan in a reverse procedure to removal. Pay attention to the direction of the fan.</p> <p>② Install the fan and fan cover on the AC drive. Note that the mounting holes are aligned, as shown in figure 3 of the removal procedure.</p> <p>③ After the replacement is complete, check that the air flow direction is upright.</p>		
<p>Note that the airflow direction is upright.</p> 		


### Removing the Fan (MD290T200G to MD290T450G, MD290T220P to MD290T500P)

- ① Remove the six screws on the cover. Then, hold the cover with both hands and lift it up in the arrow direction shown below to remove the cover.




- ② Disconnect the fan power cable connectors from the AC drive. Each fan has a power cable connector.

- ③ Remove screws from the fan box and draw the fan box out in the arrow direction.




- ④ Loosen screws from each fan cover and remove the fans.



### Installing the Fan (MD290T200G to MD290T450G, MD290T220P to MD290T500P)

- ① Install the fan in a reverse procedure to removal. Pay attention to the direction of the fan.
- ② Align the fan box to the rail and push it into the AC drive.
- ③ Connect the fan power cable connectors before fixing the fan box. After the replacement is completed, check that the air flow direction is upright.



## 7.4 Storage

For storage of the AC drive, pay attention to the following three aspects:

- 1) Pack the AC drive with the original packing box provided by Inovance.
- 2) Do not expose the AC drive to moisture, high temperature or outdoor direct sunlight for an extended period.
- 3) The electrolytic capacitor will deteriorate after being stored for a long time. Therefore, the AC drive must be switched on once every 6 months, each time for at least 5 hours. Ensure to increase the input voltage gradually to the rated value by using a voltage regulator. Contact professionals for technical support if necessary.

# Appendix A Parameter Table

☆ : It is possible to modify the parameter with the AC drive in the Stop and in the Run status.


★ : It is not possible to modify the parameter with the AC drive in the Run status.

● : The parameter is the actual measured value and cannot be modified.

\*: The parameter is a factory parameter and can be set only by the manufacturer.

## A.1 Standard Parameter Table

No.	Param. Name	Setting Range		Default	Change
Group F0: Standard Parameters					
F0-00	G/P type display	1: G (constant torque load)      2: P (fan and pump)		2	★
F0-01	Motor 1 control mode	2: V/F		2	★
F0-02	Command source selection	0: Operating panel 1: Terminal	2: Serial communication	0	☆
F0-03	Main frequency reference setting channel selection	0: Digital setting (revised value is cleared after power off) 1: Digital setting (revised value is not cleared after power off) 2: AI1 3: AI2	4: AI3 5: Pulse setting (DI5) 6: Multi-reference 7: Simple PLC 8: PID reference 9: Communication setting	0	★
F0-04	Auxiliary frequency reference setting channel selection	Same as F0-03 (Main frequency reference setting channel selection)		0	★
F0-05	Base value of range of auxiliary frequency reference for main and auxiliary calculation	0: Relative to maximum frequency	1: Relative to main frequency reference	0	☆
F0-06	Range of auxiliary frequency reference for main and auxiliary calculation	0% to 150%		100%	☆
F0-07	Final frequency reference setting selection	<div style="text-align: center;">  </div> <div style="margin-top: 10px;"> <p><b>Tens: main and auxiliary calculation formula</b>                      0: Main + auxiliary                      1: Main - auxiliary                      2: Max. (main, auxiliary)                      3: Min. (main, auxiliary)</p> <p><b>Ones: Frequency reference selection</b>                      0: Main frequency reference                      1: Main and auxiliary calculation (based on tens position)                      2: Switchover between main and auxiliary                      3: Switchover between main and "main &amp; auxiliary calculation"                      4: Switchover between auxiliary and "main &amp; auxiliary calculation"</p> </div>		00	☆
F0-08	Preset frequency	0.00 Hz to F0-10 (Max. frequency)		50.00 Hz	☆
F0-09	Running direction	0: Run in the default direction (FWD/REV indicator off)	1: Run in the direction reverse to the default direction	0	☆
F0-10	Max. frequency	50.00 Hz to 500.00 Hz		50.00 Hz	★
F0-11	Setting channel of frequency upper limit	0: Set by F0-12 (Frequency reference upper limit) 1: AI1 2: AI2	3: AI3 4: Pulse reference 5: Communication reference	0	★


No.	Param. Name	Setting Range		Default	Change
F0-12	Frequency reference upper limit	F0-14 (Frequency reference lower limit) to F0-10 (Max. frequency)		50.00 Hz	☆
F0-13	Frequency reference upper limit offset	0.00 Hz to F0-10 (Max. frequency)		0.00 Hz	☆
F0-14	Frequency reference lower limit	0.00 Hz to F0-12 (Frequency reference upper limit)		0.00 Hz	☆
F0-15	Carrier frequency	0.8 kHz to 12.0 kHz		Model dependent	☆
F0-16	Carrier frequency adjusted with load	0: Disabled	1: Enabled	1	☆
F0-17	Acceleration time 1	0.00s to 650.00s (F0-19 = 2) 0.0s to 6500.0s (F0-19 = 1)	0s to 65000s (F0-19 = 0)	Model dependent	☆
F0-18	Deceleration time 1	0.00s to 650.00s (F0-19 = 2) 0.0s to 6500.0s (F0-19 = 1)	0s to 65000s (F0-19 = 0)	Model dependent	☆
F0-19	Acceleration/Deceleration time unit	0: 1s      1: 0.1s	2: 0.01s	1	★
F0-21	Frequency offset of auxiliary frequency setting channel for main and auxiliary calculation	0.00 Hz to F0-10 (Max. frequency)		0.00 Hz	☆
F0-22	Frequency reference resolution	2: 0.01 Hz		2	★
F0-23	Retentive of digital setting frequency upon stop	0: Not retentive	1: Retentive	0	☆
F0-24	Motor parameter group selection	0: Motor parameter group 1	1: Motor parameter group 2	0	★
F0-25	Acceleration/Deceleration time base frequency	0: Maximum frequency (F0-10) 1: Frequency reference	2: 100 Hz	0	★
F0-26	Base frequency for UP/DOWN modification during running	0: Running frequency	1: Frequency reference	0	★
F0-27	Command source + frequency source			0000	☆
F0-28	Serial port communication protocol	0: Modbus protocol 1: PROFIBUS-DP or CANopen protocol		0	★
<b>Group F1: Motor 1 Parameters</b>					
F1-00	Motor type selection	0: Common asynchronous motor	1: Variable frequency asynchronous motor	0	★
F1-01	Rated motor power	0.1 kW to 1000.0 kW		Model dependent	★
F1-02	Rated motor voltage	1 V to 2000 V		Model dependent	★

Appendix A Parameter Table

No.	Param. Name	Setting Range		Default	Change
F1-03	Rated motor current	0.01 A to 655.35 A (AC drive power ≤ 55 kW) 0.1 A to 6553.5 A (AC drive power > 55 kW)		Model dependent	★
F1-04	Rated motor frequency	0.01 Hz to max. frequency		Model dependent	★
F1-05	Rated motor speed	1 rpm to 65535 rpm		Model dependent	★
F1-06	Stator resistance	0.001 Ω to 65.535 Ω (AC drive power ≤ 55 kW) 0.0001 Ω to 6.5535 Ω (AC drive power > 55 kW)		Auto-tuning parameter	★
F1-07	Rotor resistance	0.001 Ω to 65.535 Ω (AC drive power ≤ 55 kW) 0.0001 Ω to 6.5535 Ω (AC drive power > 55 kW)		Auto-tuning parameter	★
F1-08	Leakage inductive reactance	0.01 mH to 655.35 mH (AC drive power ≤ 55 kW) 0.001 mH to 65.535 mH (AC drive power > 55 kW)		Auto-tuning parameter	★
F1-09	Mutual inductive reactance	0.1 mH to 6553.5 mH (AC drive power ≤ 55 kW) 0.01 mH to 655.35 mH (AC drive power > 55 kW)		Auto-tuning parameter	★
F1-10	No-load current	0.01 A to F1-03 (AC drive power ≤ 55 kW) 0.1 A to F1-03 (AC drive power > 55 kW)		Auto-tuning parameter	★
F1-37	Auto-tuning selection	0: No auto-tuning 1: Asynchronous motor partial static auto-tuning	2: Asynchronous motor dynamic auto-tuning 3: Asynchronous motor complete static auto-tuning	0	★
<b>Group F3: V/F Control Parameters</b>					
F3-00	V/F curve setting	0, 2-9: Linear V/F 1: Multi-point V/F	10: V/F complete separation 11: V/F half separation	0	★
F3-01	Torque boost	0.0%: Automatic torque boost	0.1% to 30.0%	Model dependent	☆
F3-02	Cut-off frequency of torque boost	0.00 Hz to the maximum frequency		50.00 Hz	★
F3-03	Multi-point V/F frequency 1	0.00 Hz to F3-05 (Multi-point V/F frequency 2)		0.00 Hz	★
F3-04	Multi-point V/F voltage 1	0.0% to 100.0%		0.0%	★
F3-05	Multi-point V/F frequency 2	F3-03 (Multi-point V/F frequency 1) to F3-07 (Multi-point V/F frequency 3)		0.00 Hz	★
F3-06	Multi-point V/F voltage 2	0.0% to 100.0%		0.0%	★
F3-07	Multi-point V/F frequency 3	F3-05 (Multi-point V/F frequency 2) to F1-04 (rated motor frequency)		0.00 Hz	★
F3-08	Multi-point V/F voltage 3	0.0% to 100.0%		0.0%	★
F3-09	V/F slip compensation gain	0.0% to 200.0%		0.0%	★
F3-10	V/F over-excitation gain	0 to 200		64	☆
F3-11	V/F oscillation suppression gain	0 to 100		40	☆
F3-13	Voltage source for V/F separation	0: Set by F3-14 1: AI1 2: AI2 3: AI3 4: Pulse reference (DI5) 5: Multi-reference	6: Simple PLC 7: PID reference 8: Communication reference Note: 100.0% corresponds to the rated motor voltage.	0	☆
F3-14	Digital setting of voltage for V/F separation	0 V to rated motor voltage		0 V	☆
F3-15	Voltage rise time of V/F separation	0.0s to 1000.0s Note: It is the time used for the voltage increases from 0 V to the rated motor voltage.		0.0s	☆
F3-16	Voltage decline time of V/F separation	0.0s to 1000.0s Note: It is the time used for the voltage increases from 0 V to the rated motor voltage.		0.0s	☆
F3-17	Stop mode selection for V/F separation	0: Frequency and voltage declining to 0 independently	1: Frequency declining after voltage declines to 0	0	☆
F3-18	Current limit level	50% to 200%		150%	★

No.	Param. Name	Setting Range		Default	Change
F3-19	Current limit selection	0: Disabled	1: Enabled	1	★
F3-20	Current limit gain	0 to 100		20	☆
F3-21	Compensation factor of speed multiplying current limit	50% to 200%		50%	★
F3-22	Voltage limit	Three phase 380 to 480 V models: 330.0 to 800.0 V Three phase 200 to 240 V models: 330.0 to 800.0 V		770.0 V	★
F3-23	Voltage limit selection	0: Disabled	1: Enabled	1	★
F3-24	Frequency gain for voltage limit	0 to 100		30	☆
F3-25	Voltage gain for voltage limit	0 to 100		30	☆
F3-26	Frequency rise threshold during voltage limit	0 to 50 Hz		5 Hz	★
<b>Group F4: Input Terminals</b>					
F4-00	DI1 function selection	0: No function 1: Forward RUN (FWD) or running command	30: Pulse input (enabled only for DI5) 31: Reserved	1	★
F4-01	DI2 function selection	2: Reverse RUN (REV) or running direction (Note: F4-11 must be set when F4-00 is set to 1 or 2.)	32: Immediate DC injection braking 33: External fault normally closed (NC) input	4	★
F4-02	DI3 function selection	3: Three-wire control 4: Forward JOG (FJOG)	34: Frequency modification enabled	9	★
F4-03	DI4 function selection	5: Reverse JOG (RJOG) 6: Terminal UP	35: PID action direction reverse	12	★
F4-04	DI5 function selection	7: Terminal DOWN 8: Coast to stop	36: External STOP terminal 1 37: Running command switchover terminal 2	13	★
F4-05	DI6 function selection	9: Fault reset (RESET) 10: RUN pause	38: PID integral disabled	0	★
F4-06	DI7 function selection	11: External fault normally open (NO) input	39: Switchover between main frequency source and preset frequency	0	★
F4-07	DI8 function selection	12: Multi-reference terminal 1 13: Multi-reference terminal 2	40: Switchover between auxiliary frequency source and preset frequency	0	★
F4-08	DI9 function selection	14: Multi-reference terminal 3 15: Multi-reference terminal 4	41: Motor terminal selection 42: Reserved	0	★
F4-09	DI10 function selection	16: Terminal 1 for acceleration/deceleration time selection 17: Terminal 2 for acceleration/deceleration time selection 18: Frequency source switchover 19: UP and DOWN setting clear (terminal, operating panel) 20: Running command switchover terminal 1 21: Acceleration/Deceleration prohibited 22: PID pause 23: PLC status reset 24: Wobble pause 25: Counter input 26: Counter reset 27: Length count input 28: Length reset 29: Reserved	43: PID parameter switchover 44: User-defined fault 1 45: User-defined fault 2 46: Reserved 47: Emergency stop 48: External STOP terminal 2 49: Deceleration DC injection braking 50: Clear the current running time 51: Two-wire/Three-wire mode switchover 52-59: Reserved	0	★
F4-10	DI filter time	0.000s to 1.000s		0.010s	☆
F4-11	Terminal I/O control mode	0: Two-wire control mode 1 1: Two-wire control mode 2	2: Three-wire control mode 1 3: Three-wire control mode 2	0	★
F4-12	Terminal UP/DOWN rate	0.001 Hz/s to 65.535 Hz/s		1.00 Hz/s	☆

Appendix A Parameter Table

No.	Param. Name	Setting Range	Default	Change
F4-13	AI curve 1 min. input	0.00 V to F4-15 (AI curve 1 max. input)	0.00 V	☆
F4-14	Corresponding percentage of AI curve 1 min. input	-100.0% to +100.0%	0.0%	☆
F4-15	AI curve 1 max. input	F4-13 (AI curve 1 min. input) to 10.00 V	10.00 V	☆
F4-16	Corresponding percentage of AI curve 1 max. input	-100.0% to +100.0%	100.0%	☆
F4-17	AI1 filter time	0.00s to 10.00s	0.10s	☆
F4-18	AI curve 2 min. input	0.00 V to F4-20 (AI curve 2 max. input)	0.00 V	☆
F4-19	Corresponding percentage of AI curve 2 min. input	-100.0% to +100.0%	0.0%	☆
F4-20	AI curve 2 max. input	F4-18 (AI curve 2 min. input) to 10.00 V	10.00 V	☆
F4-21	Corresponding percentage of AI curve 2 max. input	-100.0% to +100.0%	100.0%	☆
F4-22	AI2 filter time	0.00s to 10.00s	0.10s	☆
F4-23	AI3 curve min. input	-10.00 V to F4-25 (AI curve 3 max. input)	-10.00 V	☆
F4-24	Corresponding percentage of AI curve 3 min. input	-100.0% to +100.0%	-100.0%	☆
F4-25	AI curve 3 max. input	F4-23 (AI3 curve min. input) to 10.00 V	10.00 V	☆
F4-26	Corresponding percentage of AI curve 3 max. input	-100.0% to +100.0%	100.0%	☆
F4-27	AI3 filter time	0.00s to 10.00s	0.10s	☆
F4-28	Pulse min. input	0.00 kHz to F4-30 (Pulse max. input)	0.00 kHz	☆
F4-29	Corresponding percentage of pulse min. input	-100.0% to +100.0%	0.0%	☆
F4-30	Pulse max. input	F4-28 (Pulse min. input) to 100.00 kHz	50.00 kHz	☆
F4-31	Corresponding percentage of pulse max. input	-100.0% to +100.0%	100.0%	☆
F4-32	Pulse filter time	0.00s to 10.00s	0.10s	☆
F4-33	AI curve selection		321	☆



No.	Param. Name	Setting Range	Default	Change
F4-34	Setting selection when AI less than min. input		000	☆
F4-35	DI1 delay	0.0s to 3600.0s	0.0s	★
F4-36	DI2 delay	0.0s to 3600.0s	0.0s	★
F4-37	DI3 delay	0.0s to 3600.0s	0.0s	★
F4-38	DI active mode selection 1		00000	★
F4-39	DI active mode selection 2		00000	★
F4-40	AI2 input signal selection	0: Voltage signal      1: Current signal	0	★
<b>Group F5: Output Terminals</b>				
F5-00	FM terminal output mode	0: Pulse output (FMP)      1: Digital output (FMR)	0	☆



Appendix A Parameter Table

No.	Param. Name	Setting Range		Default	Change
F5-01	FMR function selection	0: No output 1: AC drive running 2: Fault output (coast to stop) 3: Frequency-level detection FDT1 output 4: Frequency reached	23: Zero-speed running 2 (having output at stop) 24: Accumulative power-on time reached 25: Frequency level detection FDT2 output	0	☆
F5-02	Control board relay function selection (T/A-T/B-T/C)	5: Zero-speed running (no output at stop) 6: Motor overload pre-warning 7: AC drive overload pre-warning 8: Set count value reached 9: Designated count value reached	26: Frequency 1 reached 27: Frequency 2 reached 28: Current 1 reached 29: Current 2 reached 30: Timing duration reached	2	☆
F5-03	Extension card relay (P/A-P/B-P/C) function selection	10: Length reached 11: PLC cycle completed 12: Accumulative running time reached	31: AI1 input limit exceeded 32: Load lost 33: Reverse running 34: Zero current status	0	☆
F5-04	DO1 function selection	13: Frequency limited 14: Reserved	35: IGBT temperature reached 36: Software current limit exceeded	1	☆
F5-05	Extension card DO2 function selection	15: Ready for RUN 16: AI1 > AI2 17: Frequency upper limit reached 18: Frequency lower limit reached (no output at stop) 19: Undervoltage status output 20: Communication setting 21: Reserved 22: Reserved	37: Frequency lower limit reached (having output at stop) 38: Alarm output (all faults) 39: Motor overheat warning 40: Current running time reached 41: Fault output (no output at undervoltage)	4	☆
F5-06	FMP function selection	0: Running frequency 1: Set frequency 2: Output current 3: Reserved	9: AI3 (extension card) 10: Length 11: Count value 12: Communication setting	0	☆
F5-07	AO1 function selection	4: Output power 5: Output voltage 6: Pulse input (100.0% corresponds to 100.0 kHz.)	13: Motor rotational speed 14: Output current (100.0% corresponds to 1000.0 A)	0	☆
F5-08	AO2 function selection	7: AI1 8: AI2	15: Output voltage (100.0% corresponds to 1000.0 V) 16: Reserved	1	☆
F5-09	Max. FMP output frequency	0.01 kHz to 100.00 kHz		50.00 kHz	☆
F5-10	AO1 zero offset coefficient	-100.0% to +100.0%		0.0%	☆
F5-11	AO1 gain	-10.00 to +10.00		1.00	☆
F5-12	AO2 zero offset coefficient	-100.0% to +100.0%		0.0%	☆
F5-13	AO2 gain	-10.00 to +10.00		1.00	☆
F5-17	FMR output delay	0.0s to 3600.0s		0.0s	☆
F5-18	Relay 1 output delay	0.0s to 3600.0s		0.0s	☆
F5-19	Relay 2 output delay	0.0s to 3600.0s		0.0s	☆
F5-20	DO1 output delay	0.0s to 3600.0s		0.0s	☆
F5-21	DO2 output delay	0.0s to 3600.0s		0.0s	☆

No.	Param. Name	Setting Range		Default	Change
F5-22	Active mode selection of DO output terminals	<p>Ten thousands: DO2 active mode 0: Positive logic active 1: Negative logic active</p> <p>Thousands: DO1 active mode 0: Positive logic active 1: Negative logic active</p> <p>Hundreds: Relay2 active mode 0: Positive logic active 1: Negative logic active</p> <p>Tens: Relay1 active mode 0: Positive logic active 1: Negative logic active</p> <p>Ones: FMR active mode 0: Positive logic active 1: Negative logic active</p>		00000	☆
F5-23	AO1 signal selection	0: Voltage signal	1: Current signal	0	★
<b>Group F6: Start/Stop Control</b>					
F6-00	Start mode	0: Direct start	1: Flying start	0	☆
F6-01	Flying start mode	0: From stop frequency 1: From power frequency	2: From max. frequency 4: Magnetic field directional speed tracking (set F1-37 to 1 for static auto-tuning)	0	★
F6-02	Flying start speed	1 to 100		20	☆
F6-03	Start frequency	0.00 Hz to 10.00 Hz		0.00 Hz	☆
F6-04	Start frequency holding time	0.0s to 100.0s		0.0s	★
F6-05	DC injection braking level/Pre-excitation level	0% to 100%		50%	★
F6-06	DC injection braking active time/Pre-excitation active time	0.0s to 100.0s		0.0s	★
F6-07	Acceleration/Deceleration mode	0: Linear acceleration/deceleration	1-2: S-curve dynamic acceleration/deceleration	0	★
F6-08	Time proportion of S-curve start segment	0.0% to (100.0% - F6-09)		30.0%	★
F6-09	Time proportion of S-curve end segment	0.0% to (100.0% - F6-08)		30.0%	★
F6-10	Stop mode	0: Decelerate to stop	1: Coast to stop	0	☆
F6-11	DC injection braking start frequency	0.00 Hz to the maximum frequency		0.00 Hz	☆
F6-12	DC injection braking delay time	0.0s to 100.0s		0.0s	☆
F6-13	DC injection braking level	0% to 100%		50%	☆
F6-14	DC injection braking active time	0.0s to 100.0s		0.0s	☆
F6-15	Braking use ratio	0% to 100%		100%	☆
F6-18	Flying start current limit	30% to 200%		Model dependent	★
F6-21	Demagnetization time	0.00s to 15.00s		Model dependent	☆
F6-23	Overexcitation selection	0: Disabled 1: Enabled during deceleration	2: Enabled in the whole process	0	☆
F6-24	Overexcitation suppression current level	0 to 150%		100%	☆
F6-25	Overexcitation gain	1.00 to 2.50		1.25	☆



Appendix A Parameter Table

No.	Param. Name	Setting Range	Default	Change
<b>Group F7: Operating Panel and Display</b>				
F7-01	MF.K key function selection	0: MF.K key disabled 1: Switchover from remote control (terminal or communication) to operating panel control 2: Switchover between forward rotation and reverse rotation 3: Forward jog 4: Reverse jog	0	★
F7-02	STOP/RESET key function	0: STOP/RESET key enabled only in operating panel control 1: STOP/RESET key enabled in any operation mode	1	☆
F7-03	LED display running parameters 1	0000 to FFFF 	1F	☆
F7-04	LED display running parameters 2	0000 to FFFF 	33	☆


No.	Param. Name	Setting Range	Default	Change
F7-05	LED display stop parameters	0000 to FFFF 	33	☆
F7-06	Load speed display coefficient	0.0001 to 6.5000	1.0000	☆
F7-07	Heatsink temperature of IGBT	-20°C to +120°C	-	●
F7-08	Product number	-	-	●
F7-09	Accumulative running time	0h to 65535h	-	●
F7-10	Performance software version	-	-	●
F7-11	Function software version	-	-	●
F7-12	Number of decimal places for load speed display		21	☆
F7-13	Accumulative power-on time	0 to 65535h	-	●
F7-14	Accumulative power consumption	0 to 65535 kWh	-	●
<b>Group F8: Auxiliary Functions</b>				
F8-00	Jog frequency reference	0.00 Hz to the maximum frequency	2.00 Hz	☆
F8-01	Jog acceleration time	0.0s to 6500.0s	20.0s	☆
F8-02	Jog deceleration time	0.0s to 6500.0s	20.0s	☆
F8-03	Acceleration time 2	0.0s to 6500.0s	Model dependent	☆
F8-04	Deceleration time 2	0.0s to 6500.0s	Model dependent	☆
F8-05	Acceleration time 3	0.0s to 6500.0s	Model dependent	☆
F8-06	Deceleration time 3	0.0s to 6500.0s	Model dependent	☆
F8-07	Acceleration time 4	0.0s to 6500.0s	0.0s	☆
F8-08	Deceleration time 4	0.0s to 6500.0s	0.0s	☆




Appendix A Parameter Table

No.	Param. Name	Setting Range		Default	Change
F8-09	Frequency jump 1	0.00 Hz to the maximum frequency		0.00 Hz	☆
F8-10	Frequency jump 2	0.00 Hz to the maximum frequency		0.00 Hz	☆
F8-11	Frequency jump band	0.00 Hz to the maximum frequency		0.00 Hz	☆
F8-12	Forward/Reverse run switchover dead-zone time	0.0s to 3000.0s		0.0s	☆
F8-13	Reverse RUN selection	0: Disabled	1: Enabled	0	☆
F8-14	Running mode when frequency reference lower than frequency lower limit	0: Run at frequency reference lower limit 1: Stop 2: Run at zero speed		0	☆
F8-15	Droop rate	0.00% to 100.00%		0.00%	☆
F8-16	Accumulative power-on time threshold	0 to 65000h		0h	☆
F8-17	Accumulative running time threshold	0 to 65000h		0h	☆
F8-18	Startup protection selection	0: Disabled	1: Enabled	0	☆
F8-19	Frequency detection value 1	0.00 Hz to the maximum frequency		50.00 Hz	☆
F8-20	Frequency detection hysteresis 1	0.0% to 100.0% (FDT1 level)		5.0%	☆
F8-21	Detection width of target frequency reached	0.0% to 100.0% (maximum frequency)		0.0%	☆
F8-22	Jump frequency function	0: Disabled	1: Enabled	0	☆
F8-25	Switchover frequency of acceleration time 1 and acceleration time 2	0.00 Hz to the maximum frequency		0.00 Hz	☆
F8-26	Switchover frequency of deceleration time 1 and deceleration time 2	0.00 Hz to the maximum frequency		0.00 Hz	☆
F8-27	Set highest priority to terminal JOG function	0: Disabled	1: Enabled	0	☆
F8-28	Frequency detection value 2	0.00 Hz to the maximum frequency		50.00 Hz	☆
F8-29	Frequency detection hysteresis 2	0.0% to 100.0% (FDT2 level)		5.0%	☆
F8-30	Detection of frequency 1	0.00 Hz to the maximum frequency		50.00 Hz	☆
F8-31	Detection width of frequency 1	0.0% to 100.0% (maximum frequency)		0.0%	☆
F8-32	Detection of frequency 2	0.00 Hz to the maximum frequency		50.00 Hz	☆
F8-33	Detection width of frequency 2	0.0% to 100.0% (maximum frequency)		0.0%	☆
F8-34	Zero current detection level	0.0% to 300.0% 100.0% corresponds to the rated motor current.		5.0%	☆
F8-35	Zero current detection delay	0.01s to 600.00s		0.10s	☆
F8-36	Output overcurrent threshold	0.0% (no detection)	0.1% to 300.0% (rated motor current)	200.0%	☆
F8-37	Output overcurrent detection delay	0.00s to 600.00s		0.00s	☆
F8-38	Detection level of current 1	0.0% to 300.0% (rated motor current)		100.0%	☆
F8-39	Detection width of current 1	0.0% to 300.0% (rated motor current)		0.0%	☆
F8-40	Detection level of current 2	0.0% to 300.0% (rated motor current)		100.0%	☆
F8-41	Detection width of current 2	0.0% to 300.0% (rated motor current)		0.0%	☆
F8-42	Timing function	0: Disabled	1: Enabled	0	★
F8-43	Running time setting channel	0: Set by F8-44 (Running time) 1: AI1 2: AI2	3: AI3 (100% of analog input corresponds to the value of F8-44.)	0	★
F8-44	Running time	0.0 min to 6500.0 min		0.0 min	★

No.	Param. Name	Setting Range	Default	Change
F8-45	All input voltage lower limit	0.00 V to F8-46 (All input voltage upper limit)	3.10 V	☆
F8-46	All input voltage upper limit	F8-45 (All input voltage lower limit) to 10.00 V	6.80 V	☆
F8-47	IGBT temperature threshold	0°C to 100°C	75°C	☆
F8-48	Cooling fan working mode	0: Working during running      1: Working continuously	0	☆
F8-49	Wakeup frequency	F8-51 (Hibernating frequency) to F0-10 (Max. frequency)	0.00 Hz	☆
F8-50	Wakeup delay time	0.0s to 6500.0s	0.0s	☆
F8-51	Hibernating frequency	0.00 Hz to F8-49 (Wakeup frequency)	0.00 Hz	☆
F8-52	Hibernating delay time	0.0s to 6500.0s	0.0s	☆
F8-53	Running time threshold this time	0.0 to 6500.0 min	0.0 min	☆
F8-54	Output power correction coefficient	0.00% to 200.0%	100.0%	☆
F8-55	Deceleration time for emergency stop	0.00s to 650.00s (F0-19=2) 0.0s to 6500.0s (F0-19=1)	10.0s	☆
Group F9: Fault and Protection				
F9-00	Motor overload protection	0: Disabled      1: Enabled	1	☆
F9-01	Motor overload protection gain	0.20 to 10.00	1.00	☆
F9-02	Motor overload pre-warning coefficient	50% to 100%	80%	☆
F9-07	Detection of short-circuit to ground		01	☆
F9-08	Braking unit actuation voltage	Three phase 380 to 480 V models: 330.0 to 800.0 V Three phase 200 to 240 V models: 330.0 to 800.0 V	760 V	★
F9-09	Auto reset times	0 to 20	0	☆
F9-10	Selection of DO action during auto reset	0: Not act 1: Act	0	☆
F9-11	Delay of auto reset	0.1s to 100.0s	1.0s	☆
F9-12	Input phase loss/Contactor protection		11	☆


Appendix A Parameter Table

No.	Param. Name	Setting Range	Default	Change	
F9-13	Output phase loss protection		01	☆	
F9-14	1st fault type	0: No fault 1: Reserved 2: Overcurrent during acceleration 3: Overcurrent during deceleration 4: Overcurrent at constant speed 5: Overvoltage during acceleration 6: Overvoltage during deceleration 7: Overvoltage at constant speed 8: Pre-charge power fault 9: Undervoltage 10: AC drive overload 11: Motor overload 12: Input phase loss 13: Output phase loss 14: IGBT overheat 15: External fault 16: Communication fault 17: Contactor fault 18: Current detection fault 19: Motor auto-tuning fault 21: Parameter read and write fault 22: AC drive hardware fault	23: Motor short circuited to ground 24: Reserved 25: Reserved 26: Accumulative running time reached 27: User-defined fault 1 28: User-defined fault 2 29: Accumulative power-on time reached 30: Load lost 31: PID feedback lost during running 40: Fast current limit timeout 41: Motor switchover error during running 42: Reserved 43: Reserved 45: Motor overheat 55: Slave error in master-slave control	—	●
F9-15	2nd fault type		—	●	
F9-16	3rd (latest) fault type		—	●	
F9-17	Frequency upon 3rd (latest) fault	0.00 Hz to 655.35 Hz	0.00 Hz	●	
F9-18	Current upon 3rd (latest) fault	0.00 A to 655.35 A	0.00 A	●	
F9-19	Bus voltage upon 3rd (latest) fault	0.0 V to 6553.5 V	0.0 V	●	
F9-20	DI state upon 3rd (latest) fault	0 to 9999	0	●	
F9-21	DO state upon 3rd (latest) fault	0 to 9999	0	●	
F9-22	AC drive state upon 3rd (latest) fault	0 to 65535	0	●	
F9-23	Power-on time upon 3rd (latest) fault	0s to 65535s	0s	●	
F9-24	Running time upon 3rd (latest) fault	0.0s to 6553.5s	0.0s	●	
F9-27	Frequency upon 2nd fault	0.00 Hz to 655.35 Hz	0.00 Hz	●	
F9-28	Current upon 2nd fault	0.00 A to 655.35 A	0.00 A	●	
F9-29	Bus voltage upon 2nd fault	0.0 V to 6553.5 V	0.0 V	●	
F9-30	DI state upon 2nd fault	0 to 9999	0	●	
F9-31	DO state upon 2nd fault	0 to 9999	0	●	
F9-32	AC drive state upon 2nd fault	0 to 65535	0	●	
F9-33	Power-on time upon 2nd fault	0s to 65535s	0s	●	
F9-34	Running time upon 2nd fault	0.0s to 6553.5s	0.0s	●	
F9-37	Frequency upon 1st fault	0.00 Hz to 655.35 Hz	0.00 Hz	●	
F9-38	Current upon 1st fault	0.00 A to 655.35 A	0.00 A	●	
F9-39	Bus voltage upon 1st fault	0.0 V to 6553.5 V	0.0 V	●	
F9-40	DI state upon 1st fault	0 to 9999	0	●	

No.	Param. Name	Setting Range	Default	Change	
F9-41	DO state upon 1st fault	0 to 9999	0	●	
F9-42	AC drive state upon 1st fault	0 to 65535	0	●	
F9-43	Power-on time upon 1st fault	0s to 65535s	0s	●	
F9-44	Running time upon 1st fault	0.0s to 6553.5s	0.0s	●	
F9-47	Fault protection action selection 1		00000	☆	
F9-48	Fault protection action selection 2		00000	☆	
F9-49	Fault protection action selection 3		00000	☆	
F9-54	Frequency selection for continuing to run upon fault	0: Current running frequency 1: Frequency reference 2: Frequency upper limit	3: Frequency lower limit 4: Backup frequency upon abnormality	0	☆
F9-55	Backup frequency upon fault	0.0% to 100.0% (100.0% corresponds to F0-10.)	100.0%	☆	

## Appendix A Parameter Table

No.	Param. Name	Setting Range		Default	Change
F9-56	Type of motor temperature sensor	0: No temperature sensor	1: PT100 2: PT1000	0	☆
F9-57	Motor overheat protection threshold	0°C to 200°C		110°C	☆
F9-58	Motor overheat pre-warning threshold	0°C to 200°C		90°C	☆
F9-59	Power dip ride-through function selection	0: Disabled 1: Deceleration	2: Decelerate to stop	0	★
F9-60	Threshold of power dip ride-through function disabled	80% to 100%		85%	★
F9-61	Judging time of bus voltage recovering from power dip	0.0 to 100.0s		0.5s	★
F9-62	Threshold of power dip ride-through function enabled	80% to 100%		80%	★
F9-63	Load lost protection	0: Disabled	1: Enabled	0	☆
F9-64	Load lost detection level	0.0 to 100.0%		10.0%	☆
F9-65	Load lost detection time	0.0 to 60.0s		1.0s	☆
F9-67	Reserved	-		-	-
F9-68	Reserved	-		-	-
F9-69	Reserved	-		-	-
F9-70	Reserved	-		-	-
F9-71	Power dip ride-through gain Kp	0 to 100		40	☆
F9-72	Power dip ride-through integral coefficient Ki	0 to 100		30	☆
F9-73	Deceleration time of power dip ride-through	0 to 300.0s		20.0s	★
<b>Group FA: PID Function</b>					
FA-00	PID reference setting channel	0: Set by FA-01 (PID digital setting) 1: AI1 2: AI2 3: AI3	4: Pulse reference (DI5) 5: Communication reference 6: Multi-reference	0	☆
FA-01	PID digital setting	0.0% to 100.0%		50.0%	☆
FA-02	PID feedback setting channel	0: AI1 1: AI2 2: AI3 3: AI1-AI2 4: Pulse reference (DI5)	5: Communication reference 6: AI1 + AI2 7: Max. ( AI1 ,  AI2 ) 8: Min. ( AI1 ,  AI2 )	0	☆
FA-03	PID operation direction	0: Forward	1: Reverse	0	☆
FA-04	PID reference and feedback range	0 to 65535		1000	☆
FA-05	Proportional gain Kp1	0.0 to 100.0		20.0	☆
FA-06	Integral time Ti1	0.01s to 10.00s		2.00s	☆
FA-07	Differential time Td1	0.000s to 10.000s		0.000s	☆
FA-08	PID output limit in reverse direction	0.00 Hz to the maximum frequency		0.00 Hz	★
FA-09	PID error limit	0.0% to 100.0%		0.0%	☆
FA-10	PID differential limit	0.00% to 100.00%		0.10%	☆
FA-11	PID reference change time	0.00 to 650.00s		0.00s	☆
FA-12	PID feedback filter time	0.00 to 60.00s		0.00s	☆
FA-13	PID output filter time	0.00 to 60.00s		0.00s	☆
FA-14	Reserved	-		-	☆
FA-15	Proportional gain Kp2	0.0 to 1000.0		20.0	☆
FA-16	Integral time Ti2	0.01s to 10.00s		2.00s	☆
FA-17	Differential time Td2	0.000s to 10.000s		0.000s	☆


No.	Param. Name	Setting Range		Default	Change
FA-18	PID parameter switchover condition	0: No switchover 1: Switchover using DI 2: Auto switchover based on PID error	3: Auto switchover based on running frequency	0	☆
FA-19	PID error 1 for auto switchover	0.0% to FA-20 (PID error 2 for auto switchover)		20.0%	☆
FA-20	PID error 2 for auto switchover	FA-19 (PID error 1 for auto switchover) to 100.0%		80.0%	☆
FA-21	PID initial value	0.0% to 100.0%		0.0%	☆
FA-22	PID initial value active time	0.00 to 650.00s		0.00s	☆
FA-23	Forward maximum value to two output deviations	0.00% to 100.00%		1.00%	☆
FA-24	Reverse maximum value to two output deviations	0.00% to 100.00%		1.00%	☆
FA-25	PID integral property	 <p>Tens: Whether to stop integral operation when the PID output reaches the limit 0: Continue integral operation 1: Stop integral operation</p> <p>Ones: Integral separation 0: Disabled 1: Enabled</p>		00	☆
FA-26	Detection level of PID feedback loss	0.0%: No detection	0.1% to 100.0%	0.0%	☆
FA-27	Detection time of PID feedback loss	0.0s to 20.0s		0.0s	☆
FA-28	Selection of PID operation at stop	0: Disabled	1: Enabled	0	☆
<b>Group FB: Fixed Length and Count</b>					
FB-05	Set length	0 m to 65535 m		1000 m	☆
FB-06	Actual length	0 m to 65535 m		0 m	☆
FB-07	Number of pulses per meter	0.1 to 6553.5		100.0	☆
FB-08	Set count value	1 to 65535		1000	☆
FB-09	Designated count value	1 to 65535		1000	☆
<b>Group FC: Multi-Reference and Simple PLC Function</b>					
FC-00	Reference 0	-100.0% to +100.0%		0.0%	☆
FC-01	Reference 1	-100.0% to +100.0%		0.0%	☆
FC-02	Reference 2	-100.0% to +100.0%		0.0%	☆
FC-03	Reference 3	-100.0% to +100.0%		0.0%	☆
FC-04	Reference 4	-100.0% to +100.0%		0.0%	☆
FC-05	Reference 5	-100.0% to +100.0%		0.0%	☆
FC-06	Reference 6	-100.0% to +100.0%		0.0%	☆
FC-07	Reference 7	-100.0% to +100.0%		0.0%	☆
FC-08	Reference 8	-100.0% to +100.0%		0.0%	☆
FC-09	Reference 9	-100.0% to +100.0%		0.0%	☆
FC-10	Reference 10	-100.0% to +100.0%		0.0%	☆
FC-11	Reference 11	-100.0% to +100.0%		0.0%	☆
FC-12	Reference 12	-100.0% to +100.0%		0.0%	☆
FC-13	Reference 13	-100.0% to +100.0%		0.0%	☆
FC-14	Reference 14	-100.0% to +100.0%		0.0%	☆
FC-15	Reference 15	-100.0% to +100.0%		0.0%	☆
FC-16	Simple PLC running mode	0: Stop after running one cycle 1: Keep final values after running one cycle	2: Repeat after running one cycle	0	☆





Appendix A Parameter Table

No.	Param. Name	Setting Range	Default	Change
FC-17	Simple PLC retentive selection		00	☆
FC-18	Running time of simple PLC reference 0	0.0s (h) to 6553.5s (h)	0.0s (h)	☆
FC-19	Acceleration/Deceleration time of simple PLC reference 0	0 to 3	0	☆
FC-20	Running time of simple PLC reference 1	0.0s (h) to 6553.5s (h)	0.0s (h)	☆
FC-21	Acceleration/Deceleration time of simple PLC reference 1	0 to 3	0	☆
FC-22	Running time of simple PLC reference 2	0.0s (h) to 6553.5s (h)	0.0s (h)	☆
FC-23	Acceleration/Deceleration time of simple PLC reference 2	0 to 3	0	☆
FC-24	Running time of simple PLC reference 3	0.0s (h) to 6553.5s (h)	0.0s (h)	☆
FC-25	Acceleration/Deceleration time of simple PLC reference 3	0 to 3	0	☆
FC-26	Running time of simple PLC reference 4	0.0s (h) to 6553.5s (h)	0.0s (h)	☆
FC-27	Acceleration/Deceleration time of simple PLC reference 4	0 to 3	0	☆
FC-28	Running time of simple PLC reference 5	0.0s (h) to 6553.5s (h)	0.0s (h)	☆
FC-29	Acceleration/Deceleration time of simple PLC reference 5	0 to 3	0	☆
FC-30	Running time of simple PLC reference 6	0.0s (h) to 6553.5s (h)	0.0s (h)	☆
FC-31	Acceleration/Deceleration time of simple PLC reference 6	0 to 3	0	☆
FC-32	Running time of simple PLC reference 7	0.0s (h) to 6553.5s (h)	0.0s (h)	☆
FC-33	Acceleration/Deceleration time of simple PLC reference 7	0 to 3	0	☆
FC-34	Running time of simple PLC reference 8	0.0s (h) to 6553.5s (h)	0.0s (h)	☆
FC-35	Acceleration/Deceleration time of simple PLC reference 8	0 to 3	0	☆
FC-36	Running time of simple PLC reference 9	0.0s (h) to 6553.5s (h)	0.0s (h)	☆



No.	Param. Name	Setting Range		Default	Change
FC-37	Acceleration/Deceleration time of simple PLC reference 9	0 to 3		0	☆
FC-38	Running time of simple PLC reference 10	0.0s (h) to 6553.5s (h)		0.0s (h)	☆
FC-39	Acceleration/Deceleration time of simple PLC reference 10	0 to 3		0	☆
FC-40	Running time of simple PLC reference 11	0.0s (h) to 6553.5s (h)		0.0s (h)	☆
FC-41	Acceleration/Deceleration time of simple PLC reference 11	0 to 3		0	☆
FC-42	Running time of simple PLC reference 12	0.0s (h) to 6553.5s (h)		0.0s (h)	☆
FC-43	Acceleration/Deceleration time of simple PLC reference 12	0 to 3		0	☆
FC-44	Running time of simple PLC reference 13	0.0s (h) to 6553.5s (h)		0.0s (h)	☆
FC-45	Acceleration/Deceleration time of simple PLC reference 13	0 to 3		0	☆
FC-46	Running time of simple PLC reference 14	0.0s (h) to 6553.5s (h)		0.0s (h)	☆
FC-47	Acceleration/Deceleration time of simple PLC reference 14	0 to 3		0	☆
FC-48	Running time of simple PLC reference 15	0.0s (h) to 6553.5s (h)		0.0s (h)	☆
FC-49	Acceleration/Deceleration time of simple PLC reference 15	0 to 3		0	☆
FC-50	Time unit of simple PLC running	0: s	1: h	0	☆
FC-51	Reference 0 source	0: Set by FC-00 (Reference 0) 1: AI1 2: AI2 3: AI3 4: Pulse reference	5: PID 6: Set by preset frequency (F0-08), modified using terminal UP/DOWN	0	☆
<b>Group FD: Communication</b>					
FD-00	Baud rate			5005	☆

## Appendix A Parameter Table

No.	Param. Name	Setting Range	Default	Change
FD-01	Modbus data format symbol	0: No check (8,N,2) 1: Even parity check (8,E,1) 2: Odd parity check (8,O,1) 3: No check (8,N,1) (Valid for Modbus)	0	☆
FD-02	Local address	0: Broadcast address; 1 to 247 (Valid for Modbus, PROFIBUS-DP, and CANlink)	1	☆
FD-03	Modbus response delay	0 to 20 ms (Valid for Modbus)	2	☆
FD-04	Serial port communication timeout	0.0: Disabled 0.1 to 60.0s (Valid for Modbus, PROFIBUS-DP, and CANopen)	0.0	☆
FD-05	Modbus protocol selection and PROFIBUS-DP data frame	 <p>Tens: PROFIBUS-DP 0: PPO1 format 1: PPO2 format 2: PPO3 format 3: PPO5 format</p> <p>Ones: Modbus 0: Non-standard Modbus protocol 1: Standard Modbus protocol</p>	30	☆
FD-06	Current resolution read by communication	0: 0.01 A 1: 0.1 A	0	☆
FD-08	CANlink communication timeout	0.0s (Invalid) 0.1 to 60.0s	0	☆
<b>Group FE: User-Defined Parameters</b>				
FE-00	User-defined parameter 0	F0-00 to FP-xx A0-00 to Ax-xx U0-00 to U0-xx	U3-17	☆
FE-01	User-defined parameter 1		U3-18	☆
FE-02	User-defined parameter 2		F0.00	☆
FE-03	User-defined parameter 3		F0.00	☆
FE-04	User-defined parameter 4		F0.00	☆
FE-05	User-defined parameter 5		F0.00	☆
FE-06	User-defined parameter 6		F0.00	☆
FE-07	User-defined parameter 7		F0.00	☆
FE-08	User-defined parameter 8		F0.00	☆
FE-09	User-defined parameter 9		F0.00	☆
FE-10	User-defined parameter 10		F0.00	☆
FE-11	User-defined parameter 11		F0.00	☆
FE-12	User-defined parameter 12		F0.00	☆
FE-13	User-defined parameter 13		F0.00	☆
FE-14	User-defined parameter 14		F0.00	☆
FE-15	User-defined parameter 15		F0.00	☆
FE-16	User-defined parameter 16		F0.00	☆
FE-17	User-defined parameter 17		F0.00	☆
FE-18	User-defined parameter 18		F0.00	☆
FE-19	User-defined parameter 19		F0.00	☆
FE-20	User-defined parameter 20		U0-68	☆
FE-21	User-defined parameter 21		U0-69	☆
FE-22	User-defined parameter 22		F0.00	☆
FE-23	User-defined parameter 23		F0.00	☆
FE-24	User-defined parameter 24		F0.00	☆
FE-25	User-defined parameter 25		F0.00	☆
FE-26	User-defined parameter 26		F0.00	☆
FE-27	User-defined parameter 27		F0.00	☆
FE-28	User-defined parameter 28		F0.00	☆
FE-29	User-defined parameter 29	F0.00	☆	
<b>Group FP: Parameter Management</b>				
FP-00	User password	0 to 65535	0	☆

No.	Param. Name	Setting Range		Default	Change
FP-01	Parameter initialization	0: No operation 01: Restore factory parameters except motor parameters 02: Clear records	04: Back up current user parameters 501: Restore user backup parameters	0	★
FP-02	Parameter display property			11	★
FP-03	Selection of individualized parameter display			00	☆
FP-04	Selection of parameter modification	0: Disabled	1: Enabled	0	☆
<b>Group A1: Virtual DI/DO</b>					
A1-00	VDI1 function selection	0 to 59		0	★
A1-01	VDI2 function selection	0 to 59		0	★
A1-02	VDI3 function selection	0 to 59		0	★
A1-03	VDI4 function selection	0 to 59		0	★
A1-04	VDI5 function selection	0 to 59		0	★
A1-05	VDI active state setting mode			00000	★
A1-06	Selection of VDI active state			00000	★

Appendix A Parameter Table

No.	Param. Name	Setting Range	Default	Change	
A1-07	Function selection for AI1 used as DI	0 to 59	0	★	
A1-08	Function selection for AI2 used as DI	0 to 59	0	★	
A1-09	Function selection for AI3 used as DI	0 to 59	0	★	
A1-10	Active state selection for AI used as DI		000	★	
A1-11	VDO1 function selection	0: Short with physical DIx internally	1 to 41: See physical DO selection in group F5	0	☆
A1-12	VDO2 function selection	0: Short with physical DIx internally	1 to 41: See physical DO selection in group F5	0	☆
A1-13	VDO3 function selection	0: Short with physical DIx internally	1 to 41: See physical DO selection in group F5	0	☆
A1-14	VDO4 function selection	0: Short with physical DIx internally	1 to 41: See physical DO selection in group F5	0	☆
A1-15	VDO5 function selection	0: Short with physical DIx internally	1 to 41: See physical DO selection in group F5	0	☆
A1-16	VDO1 output delay	0.0s to 3600.0s	0.0s	☆	
A1-17	VDO2 output delay	0.0s to 3600.0s	0.0s	☆	
A1-18	VDO3 output delay	0.0s to 3600.0s	0.0s	☆	
A1-19	VDO4 output delay	0.0s to 3600.0s	0.0s	☆	
A1-20	VDO5 output delay	0.0s to 3600.0s	0.0s	☆	
A1-21	VDO active mode selection		00000	☆	
<b>Group A2: Motor 2 Parameters</b>					
A2-00	Motor type selection	0: Common asynchronous motor	1: Variable frequency asynchronous motor	0	★
A2-01	Rated motor power	0.1 kW to 1000.0 kW		Model dependent	★
A2-02	Rated motor voltage	1 V to 2000 V		Model dependent	★
A2-03	Rated motor current	0.01 A to 655.35 A (AC drive power ≤ 55 kW) 0.1 A to 6553.5 A (AC drive power > 55 kW)		Model dependent	★
A2-04	Rated motor frequency	0.01 Hz to the maximum frequency		Model dependent	★

No.	Param. Name	Setting Range		Default	Change
A2-05	Rated motor speed	1 rpm to 65535 rpm		Model dependent	★
A2-06	Stator resistance	0.001 Ω to 65.535 Ω (AC drive power ≤ 55 kW) 0.0001 Ω to 6.5535 Ω (AC drive power > 55 kW)		Model dependent	★
A2-07	Rotor resistance	0.001 Ω to 65.535 Ω (AC drive power ≤ 55 kW) 0.0001 Ω to 6.5535 Ω (AC drive power > 55 kW)		Model dependent	★
A2-08	Leakage inductive reactance	0.01 mH to 655.35 mH (AC drive power ≤ 55 kW) 0.001 mH to 65.535 mH (AC drive power > 55 kW)		Model dependent	★
A2-09	Mutual inductive reactance	0.1 mH to 6553.5 mH (AC drive power ≤ 55 kW) 0.01 mH to 655.35 mH (AC drive power > 55 kW)		Model dependent	★
A2-10	No-load current	0.01 A to A2-03 (AC drive power ≤ 55 kW) 0.1 A to A2-03 (AC drive power > 55 kW)		Model dependent	★
A2-62	Motor 2 control mode	2: V/F control		2	★
A2-63	Motor 2 acceleration/ deceleration time selection	0: Same to Motor 1 1: Acceleration/Deceleration time selection 1 2: Acceleration/Deceleration time selection 2	3. Acceleration/Deceleration time selection 3 4: Acceleration/Deceleration time selection 4	0	☆
A2-64	Motor 2 torque boost	0.0%: Automatic torque boost	0.1% to 30.0%	Model dependent	☆
A2-66	Motor 2 oscillation suppression gain	0 to 100		40	☆
Group A5: Control Optimization					
A5-00	DPWM switchover frequency upper limit	5.00 Hz to the maximum frequency		8.00 Hz	☆
A5-01	PWM modulation pattern	0: Asynchronous modulation	1: Synchronous modulation	0	☆
A5-02	Dead zone compensation mode selection	0: Disabled	1: Enabled (compensation mode 1)	1	☆
A5-03	Random PWM depth	0: Random PWM invalid	1 to 10: Random PWM depth	0	☆
A5-04	Overcurrent fast prevention	0: Disabled	1: Enabled	1	☆
A5-05	Current detection compensation	0 to 100		5	☆
A5-06	Undervoltage threshold	Three phase 380 to 480 V models: 140.0 to 380.0 V Three phase 200 to 240 V models: 140.0 to 380.0 V		350 V	☆
A5-08	Low speed frequency	0.0 to 8.0 kHz		0.0 kHz	☆
A5-09	Overvoltage threshold	Three phase 380 to 480 V models: 200.0 to 820.0 V Three phase 200 to 240 V models: 200.0 to 400.0 V		Model dependent	★
A5-10	Energy-conservation control	0: Disabled	1: Enabled	0	★
Group A6: AI Curve Setting					
A6-00	AI curve 4 min. input	-10.00 V to A6-02 (AI curve 4 inflection 1 input)		0.00 V	☆
A6-01	Corresponding percentage of AI curve 4 min. input	-100.0% to +100.0%		0.0%	☆
A6-02	AI curve 4 inflection 1 input	A6-00 (AI curve 4 min. input) to A6-04 (AI curve 4 inflection 2 input)		3.00 V	☆
A6-03	Corresponding percentage of AI curve 4 inflection 1 input	-100.0% to +100.0%		30.0%	☆
A6-04	AI curve 4 inflection 2 input	A6-02 (AI curve 4 inflection 1 input) to A6-06 (AI curve 4 max. input)		6.00 V	☆
A6-05	Corresponding percentage of AI curve 4 inflection 2 input	-100.0% to +100.0%		60.0%	☆
A6-06	AI curve 4 max. input	A6-04 (AI curve 4 inflection 2 input) to +10.00 V		10.00 V	☆
A6-07	Corresponding percentage of AI curve 4 max. input	-100.0% to +100.0%		100.0%	☆
A6-08	AI curve 5 min. input	-10.00 V to A6-10 (AI curve 5 inflection 1 input)		-10.00 V	☆

Appendix A Parameter Table

No.	Param. Name	Setting Range	Default	Change
A6-09	Corresponding percentage of AI curve 5 min. input	-100.0% to +100.0%	-100.0%	☆
A6-10	AI curve 5 inflection 1 input	A6-08 (AI curve 5 min. input) to A6-12 (AI curve 5 inflection 2 input)	-3.00 V	☆
A6-11	Corresponding percentage of AI curve 5 inflection 1 input	-100.0% to +100.0%	-30.0%	☆
A6-12	AI curve 5 inflection 2 input	A6-10 (AI curve 5 inflection 1 input) to A6-14 (AI curve 5 max. input)	3.00 V	☆
A6-13	Corresponding percentage of AI curve 5 inflection 2 input	-100.0% to +100.0%	30.0%	☆
A6-14	AI curve 5 max. input	A6-12 (AI curve 5 inflection 2 input) to +10.00 V	10.00 V	☆
A6-15	Corresponding percentage of AI curve 5 max. input	-100.0% to +100.0%	100.0%	☆
A6-24	Jump point of AI1 input corresponding setting	-100.0% to +100.0%	0.0%	☆
A6-25	Jump amplitude of AI1 input corresponding setting	0.0% to 100.0%	0.5%	☆
A6-26	Jump point of AI2 input corresponding setting	-100.0% to +100.0%	0.0%	☆
A6-27	Jump amplitude of AI2 input corresponding setting	0.0% to 100.0%	0.5%	☆
A6-28	Jump point of AI3 input corresponding setting	-100.0% to +100.0%	0.0%	☆
A6-29	Jump amplitude of AI3 input corresponding setting	0.0% to 100.0%	0.5%	☆
<b>Group A7: User Programmable Card</b>				
A7-00	User programmable function selection	0: Disabled 1: Enabled	0	★
A7-01	Control board output terminal control mode selection		0	★
A7-02	Programmable card AI/AO function selection	0: AI3 (voltage input), AO2 (voltage output) 1: AI3 (voltage input), AO2 (current output) 2: AI3 (current input), AO2 (voltage output) 3: AI3 (current input), AO2 (current output) 4: AI3 (PTC input), AO2 (voltage output) 5: AI3 (PTC input), AO2 (current output) 6: AI3 (PT100 input), AO2 (voltage output) 7: AI3 (PT100 input), AO2 (current output)	0	★
A7-03	FMP output	0.0% to 100.0%	0.0%	☆
A7-04	AO1 output	0.0% to 100.0%	0.0%	☆

No.	Param. Name	Setting Range	Default	Change	
A7-05	Selection of PLC program controlling digital output		1	☆	
A7-06	Setting frequency reference using the user programmable card	-100.00% to 100.00%	0.0%	☆	
A7-08	Setting running command using the user programmable card	0: No command 1: Forward run 2: Reverse run 3: Forward jog	4: Reverse jog 5: Coast to stop 6: Decelerate to stop 7: Fault reset	0	☆
A7-09	Setting torque reference with the user programmable card	0: No fault	80 to 89: User-defined fault code	0	☆
<b>Group A8: Point-to-point Communication</b>					
A8-00	Point-to-point communication	0: Disabled	1: Enabled	0	☆
A8-01	Master or slave selection	0: Master	1: Slave	0	☆
A8-02	Selection of action of the slave in point-to-point communication		000	★	
A8-03	Slave received data	1: Frequency reference	0	☆	
A8-04	Zero offset of received data (torque)	-100.00% to +100.00%	0.00%	★	
A8-05	Gain of received data (torque)	-10.00 to +100.00	1.00	★	
A8-06	Point-to-point communication interruption detection time	0.0 to 10.0s	1.0s	☆	
A8-07	Master data sending cycle in point-to-point communication	0.001 to 10.000s	0.001s	☆	
A8-08	Received data zero deviation (frequency)	-100.00% to +100.00%	0.00%	★	
A8-09	Received data gain (frequency)	-10.00 to +100.00	1.00	★	
A8-10	Anti-flywheel trip coefficient	0.00% to 100.00%	10.00%	★	
<b>Group AC: AI/AO Correction</b>					
AC-00	AI1 measured voltage 1	0.500 V to 4.000 V	Factory-corrected	☆	
AC-01	AI1 displayed voltage 1	0.500 V to 4.000 V	Factory-corrected	☆	

## Appendix A Parameter Table

No.	Param. Name	Setting Range	Default	Change
AC-02	AI1 measured voltage 2	6.000 V to 9.999 V	Factory-corrected	☆
AC-03	AI1 displayed voltage 2	6.000 V to 9.999 V	Factory-corrected	☆
AC-04	AI2 measured voltage 1	0.500 V to 4.000 V	Factory-corrected	☆
AC-05	AI2 displayed voltage 1	0.500 V to 4.000 V	Factory-corrected	☆
AC-06	AI2 measured voltage 2	6.000 V to 9.999 V	Factory-corrected	☆
AC-07	AI2 displayed voltage 2	6.000 V to 9.999 V	Factory-corrected	☆
AC-08	AI3 measured voltage 1	-9.999 V to +10.000 V	Factory-corrected	☆
AC-09	AI3 displayed voltage 1	-9.999 V to +10.000 V	Factory-corrected	☆
AC-10	AI3 measured voltage 2	-9.999 V to +10.000 V	Factory-corrected	☆
AC-11	AI3 displayed voltage 2	-9.999 V to +10.000 V	Factory-corrected	☆
AC-12	AO1 target voltage 1	0.500 V to 4.000 V	Factory-corrected	☆
AC-13	AO1 measured voltage 1	0.500 V to 4.000 V	Factory-corrected	☆
AC-14	AO1 target voltage 2	6.000 V to 9.999 V	Factory-corrected	☆
AC-15	AO1 measured voltage 2	6.000 V to 9.999 V	Factory-corrected	☆
AC-16	AO2 target voltage 1	0.500 V to 4.000 V	Factory-corrected	☆
AC-17	AO2 measured voltage 1	0.500 V to 4.000 V	Factory-corrected	☆
AC-18	AO2 target voltage 2	6.000 V to 9.999 V	Factory-corrected	☆
AC-19	AO2 measured voltage 2	6.000 V to 9.999 V	Factory-corrected	☆
AC-20	AI2 actual current 1	0.000 mA to 20.000 mA	Factory-corrected	☆
AC-21	AI2 sampling current 2	0.000 mA to 20.000 mA	Factory-corrected	☆
AC-22	AI2 actual current 2	0.000 mA to 20.000 mA	Factory-corrected	☆
AC-23	AI2 sampling current 2	0.000 mA to 20.000 mA	Factory-corrected	☆
AC-24	AO1 ideal current 1	0.000 mA to 20.000 mA	Factory-corrected	☆
AC-25	AO1 actual current 1	0.000 mA to 20.000 mA	Factory-corrected	☆
AC-26	AO1 ideal current 2	0.000 mA to 20.000 mA	Factory-corrected	☆
AC-27	AO1 actual current 2	0.000 mA to 20.000 mA	Factory-corrected	☆

## A.2 Monitoring Parameters

No.	Param. Name	Minimum Unit	Communication Address
Group U0: Monitoring Parameters			
U0-00	Running frequency	0.01 Hz	7000H
U0-01	Frequency reference	0.01 Hz	7001H
U0-02	Bus voltage	0.1 V	7002H
U0-03	Output voltage	1 V	7003H
U0-04	Output current	0.01 A	7004H
U0-05	Output power	0.1 kW	7005H
U0-06	Reserved	-	-
U0-07	DI state	1	7007H
U0-08	DO state	1	7008H
U0-09	AI1 voltage	0.01 V	7009H
U0-10	AI2 voltage (V)/current (mA)	0.01 V/0.01 mA	700AH
U0-11	AI3 voltage	0.01 V	700BH
U0-12	Count value	1	700CH
U0-13	Length value	1	700DH
U0-14	Load speed	1 rpm/min	700EH
U0-15	PID reference	1	700FH
U0-16	PID feedback	1	7010H
U0-17	PLC stage	1	7011H
U0-18	Pulse reference	0.01 kHz	7012H
U0-19	Feedback speed	0.01 Hz	7013H
U0-20	Remaining running time	0.1 min	7014H
U0-21	AI1 voltage before correction	0.001 V	7015H
U0-22	AI2 voltage (V)/current (mA) before correction	0.001 V/0.01 mA	7016H
U0-23	AI3 voltage before correction	0.001 V	7017H
U0-24	Motor speed	1 rpm/min	7018H
U0-25	Current power-on time	1 min	7019H
U0-26	Current running time	0.1 min	701AH
U0-27	Pulse reference	1 Hz	701BH
U0-28	Communication reference	0.01%	701CH
U0-30	Main frequency reference	0.01 Hz	701EH
U0-31	Auxiliary frequency reference	0.01 Hz	701FH
U0-32	Viewing any register address value	1	7020H
U0-34	Motor temperature	1°C	7022H
U0-35	Reserved	-	-
U0-36	Resolver position	1	7024H
U0-37	Power factor angle	0.1°	7025H
U0-38	ABZ position	1	7026H
U0-39	Target voltage upon V/F separation	1 V	7027H
U0-40	Output voltage upon V/F separation	1 V	7028H
U0-41	DI state display	1	7029H
U0-42	DO state display	1	702AH
U0-43	DI set for function state display 1 (function 01-40)	1	702BH

## Appendix A Parameter Table

No.	Param. Name	Minimum Unit	Communication Address
U0-44	DI set for function state display 2 (function 41-80)	1	702CH
U0-45	Fault information	1	702DH
U0-59	Rated frequency	0.01%	703BH
U0-60	Running frequency	0.01%	703CH
U0-61	AC drive state	1	703DH
U0-62	Current fault code	1	703EH
U0-63	Sending torque value of point-to-point communication	0.01%	703FH
U0-64	Number of slaves	1	7040H
U0-66	Communication extension card type	Display range	100: CANOpen 200: PROFIBUS-DP 300: CANlink
U0-67	Communication extension card version	Display range	-
U0-68	AC drive state on DP card	Display range	Bit0: AC drive running status Bit1: Running direction Bit2: Whether the AC drive has a fault Bit3: Target frequency reached Bit4 to Bit7: Reserved Bit8 to Bit15: Fault code
U0-69	Speed of transmitting DP/0.01 Hz	Display range	0.00 Hz to the maximum frequency
U0-70	Motor speed of transmitting DP/RMP	Display range	0 to 65535
U0-71	Communication card current display	Display range	-
U0-72	Communication card faulty state	Display range	-
U0-73	Motor SN	Display range	0: Motor 1 1: Motor 2
U0-76	Low bits of accumulative power consumption	0.1°	704CH
U0-77	High bits of accumulative power consumption	1°	704DH
U0-78	Linear speed	1 m/min	704EH

# INOVANCE Warranty Agreement

- 1) Inovance provides an 18-month free warranty to the equipment itself from the date of manufacturing for the failure or damage under normal use conditions.
- 2) Within the warranty period, maintenance will be charged for the damage caused by the following reasons:
  - a. Improper use or repair/modification without prior permission
  - b. Fire, flood, abnormal voltage, natural disasters and secondary disasters
  - c. Hardware damage caused by dropping or transportation after procurement
  - d. Operations not following the user instructions
  - e. Damage out of the equipment (for example, external device factors)
- 3) The maintenance fee is charged according to the latest Maintenance Price List of Inovance.
- 4) If there is any problem during the service, contact Inovance's agent or Inovance directly.
- 5) Inovance reserves the rights for explanation of this agreement.

Suzhou Inovance Technology Co., Ltd.

Address: No.16, Youxiang Road, Yuexi Town, Wuzhong District, Suzhou 215104, P.R. China

Website: <http://www.inovance.com>

## Shenzhen Inovance Technology Co., Ltd.

Add.: Building E, Hongwei Industry Park, Liuxian Road, Baocheng No. 70 Zone, Bao' an District, Shenzhen

Tel: +86-755-2979 9595

Fax: +86-755-2961 9897

<http://www.inovance.com>

## Suzhou Inovance Technology Co., Ltd.

Add.: No. 16 Youxiang Road, Yuexi Town, Wuzhong District, Suzhou 215104, P.R. China

Tel: +86-512-6637 6666

Fax: +86-512-6285 6720

<http://www.inovance.com>



19010376A05